

UCS Central註冊和故障排除

目錄

[簡介](#)

[採用元件](#)

[程式](#)

[常見註冊問題故障排除：](#)

[案例 1:從UCS中心註冊域時，UCS域的管理員密碼錯誤。](#)

[案例 2:UCS中心和UCS域時間未同步。](#)

[案例 3:從UCS域註冊時輸入的共用金鑰錯誤。](#)

[案例 4:註冊期間，UCS Central無法與UCS Manager通訊](#)

簡介

本文檔介紹向UCS Central註冊思科統一計算系統 — UCS域的步驟。在UCS Central 1.5版之前，只能從UCS Manager進行註冊。從1.5版本起，可以從UCS Central和UCS Manager進行註冊。

採用元件

UCS Central 2.0(1a)

UCS管理器3.1(3a)

使用的所有裝置都是實驗室裝置

程式

來自UCS域的註冊流程：

啟動UCS Manager，然後按一下Admin-> Communication Management-> UCS Central。

選擇向UCS Central註冊。

輸入 UCS Central 的主機名/IP 地址和共用金鑰 (始終是使用主機名註冊 UCS Central 的最佳實踐 , 因為在註冊域時可以使用 DNS 條目更改 IP 地址) , 然後按一下 **Ok** 開始註冊。

註冊時可以設置策略解析控制。也可以在註冊後更改。

Register With UCS Central



Hostname/IP Address :

Shared Secret :

All Global

Policy Resolution Control

Infrastructure & Catalog Firmware :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the Capability Catalog and infrastructure firmware policy are defined locally or come from Cisco UCS Central.
Time Zone Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the time zone and NTP server settings are defined locally or comes from Cisco UCS Central.
Communication Services :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether HTTP, CIM XML, Telnet, SNMP, web session limits, and Management Interfaces Monitoring Policy settings are defined locally or in Cisco UCS Central.
Global Fault Policy :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the Global Fault Policy is defined locally or in Cisco UCS Central.
User Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether authentication and native domains, LDAP, RADIUS, TACACS+, trusted points, locales, and user roles are defined locally or in Cisco UCS Central.
DNS Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether DNS servers are defined locally or in Cisco UCS Central.

OK Cancel

Register With UCS Central



Hostname/IP Address :

Shared Secret :

All Global

Policy Resolution Control

Infrastructure & Catalog Firmware :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the Capability Catalog and infrastructure firmware policy are defined locally or come from Cisco UCS Central.
Time Zone Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the time zone and NTP server settings are defined locally or comes from Cisco UCS Central.
Communication Services :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether HTTP, CIM XML, Telnet, SNMP, web session limits, and Management Interfaces Monitoring Policy settings are defined locally or in Cisco UCS Central.
Global Fault Policy :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether the Global Fault Policy is defined locally or in Cisco UCS Central.
User Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether authentication and native domains, LDAP, RADIUS, TACACS+, trusted points, locales, and user roles are defined locally or in Cisco UCS Central.
DNS Management :	<input checked="" type="radio"/> Local <input type="radio"/> Global	Determines whether DNS servers are defined locally or in Cisco UCS Central.

OK

Cancel

監控FSM(有限狀態機)狀態以檢查註冊過程。

All / Communication Management / UCS Central

UCS Central Providers FSM Faults


UCS Central Registration Policy Resolution Control

FSM Status : **Success**

Description :

Current FSM Name : **Register Fsm**

Completed at : **2017-08-18T13:02:42Z**

Progress Status :  100%

Remote Invocation Result : **Not Applicable**

Remote Invocation Error Code : **None**


Remote Invocation Description :

Step Sequence


Order	Name	Description	Status	Timestamp	Retried
1	Register Fsm Execute	Register FSM Execute(FS...	Success	2017-08-18T13:02:42Z	2

UCS Central的註冊流程：

啟動UCS Central，點選System tools(系統工具)，然後轉至Domain Management(域管理)。



按一下右角的**Register Domain**。



輸入UCS域主機名/IP地址以及管理員使用者名和密碼。選擇UCS Central的主機名/IP地址 (Hostname/IP Address)，然後按一下**Register** (註冊)。(在註冊域時，始終使用主機名作為IP地址註冊UCS中心的最佳做法是使用DNS條目進行更改)。

Domain to UCS Central Register



- Policy
- Resolution
- Control

UCS Central System Profile - Date & Time

In addition, if HTTPS is supported on the Domain, it must be enabled in order to register with UCS Central.

UCS Domain Hostname/IP Address *

ucsdomain.cisco.com

UCS Domain User Name *

admin

UCS Domain Password

Registration Hostname/IP address from UCS Central

hk-central-2

Cisco best practice is to register UCS Domains to UCS Central using the Fully Qualified Domain Name (FQDN). If you register the UCS Domain to UCS Central using an IP address and later change the IP address of UCS Central, you will need to unregister and re-register the UCS Domain to UCS Central.

[UCS Central System Profile - DNS](#)

Cancel

Register

可以從Configuration Status頁籤監控FSM狀態。

Register Domain

Filter Export Delete Unregister Domain

<input type="checkbox"/>	UCS Domain	Timestamp	Registration Status	Q
<input type="checkbox"/>	172.16.16.153	17-Aug-2017 3:42:05 PM	In Progress Configuration Status	

常見註冊問題故障排除：

案例 1:從UCS中心註冊域時，UCS域的管理員密碼錯誤。

修正:請更正管理員密碼，然後重試註冊。

來自UCS Central的FSM狀態

Domain Registrations Configuration Status



System FSM Name Registration Fail	Status Registration Fail	Progress Status <div style="width: 10%;"><div style="width: 10%;"></div></div> 10%	FSM Details		
Current Stage Name Authorizing Admin Credentials	Stage Status Failed	Retries 1	Time Stamp 17-Aug-2017 3:40:54 PM		
Order	Name	Description	Timestamp	Retries	Status
3	Remote Domain Reg Check Status			0	Skipped
2	Remote Domain Reg Push Shared Secret			0	Skipped
1	Authorizing Admin Credentials	Authorizing the admin credentials against the remote domain(FSM-STAGE:sam:dme:PolicyControlEpOpRemoteDomainReg:Registration)	17-Aug-2017 3:40:54 PM	1	Failed

Close

案例 2:UCS中心和UCS域時間未同步。

修正:同步UCS中心和UCS域上的時間，然後重試註冊。

請參閱以下連結中的UCS Manager中的強制時間同步以更正時間。

https://www.cisco.com/c/en/us/td/docs/unified_computing/ucs/ucs-central/GUI-User-Guides/Operations/b_UCSC_Ops_Guide_2_0/b_UCSC_Ops_Guide_2_0_chapter_01100.html

來自UCS Manager的FSM狀態

FSM Status : **In Progress**
 Description :
 Current FSM Name : **Repair Cert**
 Completed at :
 Progress Status :
 Remote Invocation Result : **Resource Unavailable**
 Remote Invocation Error Code : **5**
 Remote Invocation Description : **UCSM and UCS Central time is not synchronized. Retrying...**

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:41:53Z	1
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0

案例 3:從UCS域註冊時輸入的共用金鑰錯誤。

修正:請輸入正確的共用金鑰，然後重試註冊。

請參閱以下連結中的**重置共用金鑰**以更改共用金鑰。

https://www.cisco.com/c/en/us/td/docs/unified_computing/ucs/ucs-central/install-upgrade/2-0/b_Cisco_UCSC_Install_and_Upgrade_Guide_2_0/b_Cisco_UCSC_Install_and_Upgrade_Guide_2_0_chapter_0101.html#task_8299DFA4853049068C7E384F5E8FF493

來自UCS Manager的FSM狀態

UCS Central Providers **FSM** Faults

UCS Central Registration Policy Resolution Control

FSM Status : **Fail**
 Description :
 Current FSM Name : **Repair Cert**
 Completed at : **2017-08-17T22:45:38Z**
 Progress Status :
 Remote Invocation Result : **Failure**
 Remote Invocation Error Code : **5**
 Remote Invocation Description : **shared secret mismatch**

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:43:10Z	2
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0

案例 4:註冊期間，UCS Central無法與UCS Manager通訊

修正:確保UCSM和UCS Central over 443之間沒有防火牆阻止通訊。

來自UCS Manager的FSM狀態

UCS Central Providers **FSM** Faults

UCS Central Registration Policy Resolution Control

FSM Status : **In Progress**
 Description :
 Current FSM Name : **Repair Cert**
 Completed at :
 Progress Status :
 Remote Invocation Result : **Not Applicable**
 Remote Invocation Error Code : **None**
 Remote Invocation Description :

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:49:34Z	1
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0