

يكلساللا عيزوتلا ماظن نيوكت ةيفي RV130W ىلع (WDS)

فدهلا

لوصول طاقنل يكلساللا ليصوتلا حيتي ماظن وه (WDS) يكلساللا عيزوتلا ماظن لوصول طاقن مادختساب ةيكلساللا ةكبشلا عيسوتب WDS حمسي ام ةكبش في (AP) نيوكت بجي، WDS طايترا عاشنل اهلصول يكلساللا زاهج ىل ةجالحا نود ةددعتم ةانقلاو ةيكلساللا ةكبشلا عضو سفن في دعب نع WDS في نيخالل اارظنلاو زاهجلا ل تلحا (WEP او ايشال) ريفشلا عاون او يكلساللا قاطنلا ديدحتو ةيكلساللا [RV130W لىلع دادعلا ةيلمع ياساسا يكلساللا لكشي](#)، ةمولعم ريثك

عضو او Bridge عضو في WDS نيوكت كنكمي، ةجذومنلا ةريغصلا تاكشلا ةئيبي في ةراشا عيسوتب نيخالل لوصول طاقن موقت نا ديرت تنك اذا رسجلا عضو ديفي. رركم نا ديرت تنك اذا اديفم رركم عضو نوكي. كرتشم طبارك لمعت نيخالل، كزاهج ةكبشلا ليصوت مادختساب نيخالل لوصول طاقنل ةكبشلا ةراشا رركم كزاهج لمعي يكلسال.

RV130W ىلع يكلساللا عيزوتلا ماظن نيوكت ةيفي حيصوت وه دنتسملا اذه نم فدهلا.

قيبطتلا ةلباقلا ةزهجال

·RV130W زارطلا

جماربالا رادصا

·v1.0.1.3

يكلساللا عيزوتلا ماظن نيوكت

رسجلا عضو في WDS نيوكت

> يكلساللا رتخاو بيولا نيوكتلا ةدعاسملا ةادالا ىل لوخدلا ليچستب مق 1. ةوطخلا WDS: ةحفص حتف متي.

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Show Available Networks

MAC

Save

Cancel

WDS لوقح ي ف راي تخال اة ناخ ددح ، WDS نني كمتل 2. ة و ط خ ل ا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode

WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

WDS نڤوكت م تي امدنع **WDS Bridge** ءاقتنا رزىلع رقنا ، ءلاجل لقح ي ف 3 ةوطخلال اهنڤوكت م تي لال لوصول ءطقن نڤي عي WDS ن اف ، رسچال ءضو لىل ءجوملاب ءصاخال ءدءتم لوصول طاقن نڤب كرتشم طابتراك .

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

MAC ناونع لخدأ، دي عبلا يكلساللا رسجلاب صاخلا MAC ناونع مسق يف 4. ةوطخلا لوصو طاقن نيوكت اضيا كنكمي. MAC 1 لوقح يف رسجك همادختسال لوصولا ةطقنل Mac 2، و MAC 3، و MAC 4 لوقح يف روسجك همادختسال ةيفاضا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Show Available Networks

MAC

Save

Cancel

تاریخ تال طحل طفح قوف رقنا 5. ةوطخلا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

يكلسال رركم عضو في WDS نيوكت

> يكلسال رتخاو بيولا نيوكتل دعاملا اءالالى لولودلا ليجستب مق 1. ةوطخال WDS. ةحفصحت متي.

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

WDS لوقح ي ف راي تخالال ة ناخ ددح ، WDS نني كمتل 2. ة و ط خ ل ا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode

WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

هجوم لابل ةصاخلا WDS نڤوكت دنع WDS رركم رزى لىل عرقنا ،عضول ل قح يف 3. ةوطخلا طاقن ب لىصوت لىل اهنڤوكت مت ڤىل ل لوصول ةطقن نڤىع يف WDS نإف ،رركم عضو لىل تاراش إلا راركت لال خ نم (LAN) ةلحم لال ةكبش لابل ڤىكلس لاصتا نودب ةددعتم لوصول ڤىكلس لال لاصتا لال مادختساب .

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

ىل عةحاتملا تارايلخا ديحت متي. WDS رركم عوضول بوغرملا رايلخا رتخأ. 4 ةوطخلا
يلتال وحنلا:

لوصو طاقن مادختسا متي — رركم ةطساوب ةيكلساللا ةراشإلا راركتب حامسلا
ةيكلساللا زاهجلا ةراشإ راركتل ةنيعم.

ةراشإلا راركتل زاهجلا مدختسي — دعب نع لوصولا ةطقنل ةيكلساللا ةراشإلا راركت
يطختلاب مقف، رايلخا اذه ديحتب تمق اذا. ىرخأ ةيكلسال لوصو ةطقنل ةيكلساللا
6 ةوطخلا ىل.

4 ةوطخلا ي ف رركم ةطساوب ةيكلساللا ةراشإلا راركتب حامسلا ترتخأ اذا. 5 ةوطخلا
طاقن نيوكت كنكمي. MAC 1 لققح ي ف رركمك مدختستل لوصو ةطقنل MAC ناوع لخدأ
يطختلا. MAC 4، و MAC 3، و MAC 2 لوقح ي ف راركت زهجاك اهمادختسال ةيفاضا لوصو
9 ةوطخلا ىل.

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save

Cancel

رقنا 4، ةوطخلال في دعب نع لوصول ةطقنل ةيكلسالل ةراشلل راركت ترتخأ اذا 6. ةوطخلال ةحاتملا ةيكلسالل لوصول طاقن ىلع روثعلل ةحاتملا تاكبشلل راهظ ىلع اهب ليصوتلل.

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

قحاتملا تاكبشلا لودج رهظي

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Available Networks Table

	Network Name (SSID)	Channel	Security	Signal	MAC Address
<input type="checkbox"/>	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
<input type="checkbox"/>	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
<input type="checkbox"/>	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
<input type="checkbox"/>	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
<input type="checkbox"/>	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
<input type="checkbox"/>	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
<input type="checkbox"/>	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

لوصولا ةطقن ديدحتل ةكبشلا مسال ةبوغرملا رايتخاله ةناخ ددح 7 ةوطخال
اهب ةصخاله ةراشاله زاھجل رركي نا ديرت يتل ةحاتملا ةيكلسالل

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
<input checked="" type="checkbox"/>	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
<input type="checkbox"/>	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
<input type="checkbox"/>	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
<input type="checkbox"/>	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
<input type="checkbox"/>	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
<input type="checkbox"/>	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
<input type="checkbox"/>	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

Connect Refresh

MAC

MAC لوجح ىل ةددمال لوصول ةطقنل MAC ناوع ةفاضل لىصوت رزرقنا 8 ةوطخلا

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
<input checked="" type="checkbox"/>	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
<input type="checkbox"/>	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
<input type="checkbox"/>	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
<input type="checkbox"/>	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
<input type="checkbox"/>	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
<input type="checkbox"/>	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
<input type="checkbox"/>	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

Connect Refresh

MAC

ةددمال ةكبشلل MAC ناوعب MAC لوجح شىدحت متيس.

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
<input checked="" type="checkbox"/>	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
<input type="checkbox"/>	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
<input type="checkbox"/>	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
<input type="checkbox"/>	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
<input type="checkbox"/>	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
<input type="checkbox"/>	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
<input type="checkbox"/>	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

ك.ت اداع | ظ فحل ظ فح يل ع رقنا .9 ة و ط خ ل ا

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
<input checked="" type="checkbox"/>	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
<input type="checkbox"/>	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
<input type="checkbox"/>	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
<input type="checkbox"/>	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
<input type="checkbox"/>	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
<input type="checkbox"/>	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
<input type="checkbox"/>	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذه Cisco تچرت
ملاعلاء انءمچ يف نيمدختسمل معدى وتحم مي دقتل ةيرشبلاو
امك ةقيد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچرئ. ةصاغل مهتغب
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه
ىلإ أمئاد ةوچرلاب يصوت وتامچرتل هذه ةقد نع اهتيلوئسم Cisco
Systems (رفوتم طبارلا) يلصلأل يزي لچنل دن تسمل