



Cisco vWAAS with Akamai Connect

This chapter provides an overview of Cisco vWAAS with Akamai Connect, and describes the hardware requirements for Cisco vWAAS with Akamai Connect, including how to upgrade Cisco vWAAS memory and disk for the Akamai cache engine.

This chapter contains the following sections:

- [About Cisco vWAAS with Akamai Connect, on page 1](#)
- [Supported Platforms for Cisco vWAAS with Akamai Connect, on page 2](#)
- [Cisco vWAAS with Akamai Connect License, on page 3](#)
- [Cisco vWAAS with Akamai Connect Hardware Requirements, on page 4](#)
- [Upgrading vWAAS Memory and Disk for Akamai Connect, on page 5](#)
- [Cisco vWAAS-150 with Akamai Connect, on page 9](#)
- [Akamai Connect Cache Engine on Cisco Mid-End and High-End Platforms, on page 10](#)

About Cisco vWAAS with Akamai Connect

Akamai Connect is the HTTP/S object cache component added to Cisco WAAS, integrated into the existing WAAS software stack and leveraged via the HTTP Application Optimizer.

- Cisco WAAS with Akamai Connect helps to reduce latency for HTTP/S traffic for business and web applications, and can improve performance for many applications, including Point of Sale (POS), HD video, digital signage, and in-store order processing.
- Cisco WAAS with Akamai Connect provides significant and measurable WAN data offload, and is compatible with existing WAAS functions such as DRE (deduplication), LZ (compression), TFO (Transport Flow Optimization), and SSL acceleration (secure/encrypted) for first and second pass acceleration.
- For more information on Cisco WAAS with Akamai Connect, see the chapter "Configuring Cisco WAAS with Akamai Connect" in the [Cisco Wide Area Application Services Configuration Guide](#).

Cisco vWAAS in Cisco WAAS with Akamai Connect is an integrated solution that combines WAN optimization and intelligent object caching to accelerate HTTP/S applications, video, and content.

Cisco vWAAS in Cisco WAAS with Akamai Connect helps reduce latency for HTTP/HTTPS traffic for business and web applications, and can improve performance for many applications, including Point of Sale (POS), HD video, digital signage, and in-store order processing. It provides significant and measurable WAN

data offload, and is compatible with existing Cisco WAAS functions such as DRE, LZ, TFO, and SSL acceleration for first and second pass acceleration.

For more information, see the "Configuring Application Acceleration" chapter of the [Cisco Wide Area Application Services Configuration Guide](#).

Supported Platforms for Cisco vWAAS with Akamai Connect

The following table shows supported platforms for Cisco vWAAS with Akamai Connect, up to 6,000 connections.

Table 1: Supported Cisco Devices for Akamai Caching, Up to 6,000 Connections

Cisco vWAAS	Cisco ISR-WAAS	Cisco WAVE	Cisco SRE-SM (for WAAS Version 6.2.x and earlier)
vWAAS-150 (for Cisco WAAS Version 6.1.1 and later)	<ul style="list-style-type: none"> • ISR-G2 • ISR-G3 	<ul style="list-style-type: none"> • N/A 	<ul style="list-style-type: none"> • N/A
vWAAS-200	<ul style="list-style-type: none"> • ISR-WAAS-750 • ISR-4451 • ISR-4431 • ISR-4351 • ISR-4331 • ISR-4321 	<ul style="list-style-type: none"> • WAVE-294 	<ul style="list-style-type: none"> • SRE-SM-700
vWAAS-750	<ul style="list-style-type: none"> • ISR-WAAS-1300 • ISR-4451 • ISR-4431 	<ul style="list-style-type: none"> • WAVE-594 	<ul style="list-style-type: none"> • SRE-SM-900
vWAAS-1300	<ul style="list-style-type: none"> • ISR-WAAS-2500 • ISR-4451 	<ul style="list-style-type: none"> • WAVE-694 	<ul style="list-style-type: none"> • SRE-SM-710
vWAAS-2500	<ul style="list-style-type: none"> • N/A 	<ul style="list-style-type: none"> • N/A 	<ul style="list-style-type: none"> • SRE-SM-910
vWAAS-6000	<ul style="list-style-type: none"> • N/A 	<ul style="list-style-type: none"> • N/A 	<ul style="list-style-type: none"> • N/A

The following table shows supported platforms for Cisco vWAAS with Akamai Connect, beyond 6,000 connections

Table 2: Supported Cisco vWAAS Models for Akamai Caching, Beyond 6,000 Connections

Cisco vWAAS Model	Total HTTP Object Cache Connections	Cache Engine Cache Disk	Additional Resource to be Added
vWAAS-12000	12,000	750 GB	6 GB RAM, 750 GB disk
vWAAS-50000	50,000	850 GB	850 GB disk



Note In Cisco vWAAS in WAAS Version 6.2.x, Cisco vWAAS with Akamai Connect beyond 6,000 connections is not supported for Cisco vWAAS on RHEL KVM or KVM on CentOS.

Cisco vWAAS with Akamai Connect License

Cisco iWAN with Akamai Connect is an advanced license that you can add to Cisco WAAS. The license for Cisco iWAN with Akamai Connect is aligned with the number of optimized connections in each supported Cisco WAAS model.

The following table lists the standalone licenses for Cisco iWAN with Akamai Connect and vWAAS. For information on all licenses for Cisco iWAN with Akamai Connect, see the [Cisco Intelligent WAN with Akamai Connect Data Sheet](#).



Note The actual number of connections for each Cisco iWAN with Akamai Connect License shown in the following table is dependent on the hardware module on which Cisco WAAS is running.

Table 3: Licenses for Cisco iWAN with Akamai Connect with vWAAS

Cisco iWAN with Akamai Connect License	License Description	Supported Platforms(vWAAS platforms in bolded text)
SL-1300-AKC	Akamai Connect license for up to 1,300 WAAS connections	<ul style="list-style-type: none"> • ISR-2900 or ISR-3900 and one of the following: vWAAS-1300 or lower (UCS-E) • ISR-4451, ISR-4431, ISR-4351, or ISR-4331: vWAAS-2500 or lower • UCS server: vWAAS-1300 or lower • WAVE-594

Cisco IWAN with Akamai Connect License	License Description	Supported Platforms(vWAAS platforms in bolded text)
SL-2500-AKC	Akamai Connect license for up to 2,500 WAAS connections	<ul style="list-style-type: none"> • ISR-2900 or ISR-3900 and one of the following: vWAAS-2500 or lower (UCS-E) • ISR-4451: vWAAS-2500 or lower • UCS server: vWAAS-2500 or lower • WAVE-694
SL-6000-AKC	Akamai Connect license for up to 6,000 WAAS connections	<ul style="list-style-type: none"> • ISR-2900/ISR-3900 and one of the following: vWAAS-6000 or lower (UCS-E) • UCS server: vWAAS-6000 or lower • WAVE-694

Cisco vWAAS with Akamai Connect Hardware Requirements

The following table shows the hardware requirements for Cisco UCS E-Series and Cisco ISR-WAAS for Cisco vWAAS with Akamai Connect.



Note For information on hardware requirements for vWAAS with Akamai Connect on Hyper-V, see [Configuring GPT Disk Format for vWAAS-50000 on Hyper-V with Akamai Connect](#) in the chapter "Cisco vWAAS on Microsoft Hyper-V."

Table 4: Hardware Requirements for vWAAS with Akamai Connect

Cisco vWAAS or WAAS Model	Memory Required for vWAAS with Akamai Connect	Disk Required for vWAAS with Akamai Connect
vWAAS-150	4 GB	160 GB
vWAAS-200	4 GB	260 GB
vWAAS-750	4 GB	500 GB
vWAAS-1300	6 GB	600 GB
vWAAS-2500	8 GB	750 GB

Cisco vWAAS or WAAS Model	Memory Required for vWAAS with Akamai Connect	Disk Required for vWAAS with Akamai Connect
vWAAS-6000	11 GB	900 GB
vWAAS-12000	18 GB	1500 GB
vWAAS-50000	48 GB	2350 GB
ISR-WAAS-200	2 GB	170 GB
ISR-WAAS-750	4 GB	170 GB
ISR-WAAS-1300	6 GB	170 GB
ISR-WAAS-2500	8 GB	360 GB

For more information on cache engine memory requirements and cache engine disk requirements, see [Akamai Connect Cache Engine on Cisco Mid-End and High-End Platforms](#), on page 10.

Upgrading vWAAS Memory and Disk for Akamai Connect

This section contains the following sections:

Upgrading Memory and Disk for Earlier Versions of Cisco vWAAS with Akamai Connect

Before you begin



Note The following procedure is for Cisco WAAS systems running a Cisco WAAS version earlier than Cisco WAAS Version 6.1.1. If Cisco vWAAS in Cisco WAAS Version 6.1.1 or later is running on your Cisco WAAS system, the Akamai disk is added by default, and you do not need to use the following installation procedure.

If you are running Cisco vWAAS in an early Cisco WAAS version with the following parameters, and want to upgrade to Cisco WAAS Version 5.4.1, 5.5.1, or 6.1.1, use the update memory and disk procedure to as described in the [Cisco Wide Area Application Services Release Note](#) for the specified Cisco WAAS version.

- A Cisco WAAS version earlier than Cisco WAAS Version 5.4.1
- A VMware ESXi version earlier than VMware ESXi Version 5.0

Procedure

- Step 1** Power off the Cisco vWAAS.
- Step 2** Right-click the Cisco vWAAS and select **Editing Settings...**

- Step 3** Click **Add...**
- Step 4** In the **Add Hardware** dialog box, select **Hard Disk** and click **Next**.
- Step 5** In the **Select a Disk** dialog box, select **Create a new virtual disk** and click **Next**.
- Step 6** In the **Create a Disk** dialog box:
- From the **Capacity** drop-down list, choose the size of the new disk.
 - From the **Disk Provisioning** drop-down list, choose **Thick Provision Lazy Zeroed**.
 - From the **Location** drop-down list, choose **Store with the virtual machine**.
 - Click **Next**.
- Step 7** In the **Advanced Options** dialog box:
- From the **Virtual Device Node** drop-down list, choose **SCSI (0:2)**.
 - From the **Mode** drop-down list, choose **Persistent**.
 - Click **Next**.
- Step 8** In the **Ready to Complete** dialog box, confirm the following options:
- Hardware type
 - Create disk
 - Disk capacity
 - Disk provisioning
 - Datastore
 - Virtual Device Node
 - Disk mode
- Step 9** Click **Finish**.
- The window displays the status message **New hard Disk (adding)**.
- Step 10** Click **OK**.
- Step 11** Wait until the **Recent Tasks** window displays the **Reconfigure Virtual** machine task as **Completed**, and then power on the Cisco vWAAS.
- Step 12** To verify the new disk, display the current hardware listing with **Virtual Machine Properties > Hardware**.
-

Upgrading vWAAS Memory and Disk for Cisco vWAAS-12000 with VMware ESXi

Before you begin

When the Cisco vWAAS-12000 is deployed, the RAM size is 12 GB and the `/local/local1` directory size is 15 GB. When you enable Akamai Connect for Cisco vWAAS, increase the RAM to 18 GB.



Note This procedure alters the calculation of the `local1` directory size for the vWAAS-12000 because the expected size is 27 GB. The mismatch between the existing size (15 GB) for the `local1` directory and the expected size (27 GB) triggers an alarm.

The mismatch between RAM size and disk size may cause a serious problem during a kernel crash in the Cisco vWAAS-12000, because the `vmcore` file will then be larger than what could be stored in the `local1` directory.

To avoid the scenario described in the above Note, and to safely upgrade vWAAS memory and disk for Akamai Connect for the Cisco vWAAS-12000, use the following procedure:

Procedure

Step 1 Power off the Cisco vWAAS VM.

Step 2 Add an additional disk of the required size for your system.

Step 3 Increase the size of the RAM.

Note To run Akamai Connect on Cisco vWAAS-12000, increase the size of the RAM by at least 6 GB.

Step 4 Power on the Cisco vWAAS VM.

Step 5 Check the alarms.

The `filesystem_size_mism` alarm is raised:

Critical Alarms

Alarm ID	Module/Submodule	Instance
1 filesystem_size_mism	disk	Filesystem size

Step 6 Run the `disk delete-data-partitions` command.

Note The `disk delete-data-partitions` command deletes the cache files, including DRE cache files.

Step 7 Reload the device.

- After running the `disk delete-data-partitions` command, you must reload the device.

The reload process automatically re-creates data partitions, and initializes the caches. This process may take several minutes.

DRE optimization will not start until the DRE cache has finished initializing.

Upgrading vWAAS Memory and Disk for Cisco vWAAS-12000 with Microsoft Hyper-V

Before you begin

When the Cisco vWAAS-12000 is deployed, the RAM size is 12 GB and the `/local/local1` directory size is 15 GB. When you enable Akamai Connect for Cisco vWAAS, increase the RAM to 18 GB.



Note This procedure alters the calculation of the `local1` directory size for the vWAAS-12000 because the expected size is 27 GB. The mismatch between the existing size (15 GB) for the `local1` directory and the expected size (27 GB) triggers an alarm.

The mismatch between RAM size and disk size may cause a serious problem during a kernel crash in the Cisco vWAAS-12000, because the `vmcore` file will then be larger than what could be stored in the `local1` directory.

To avoid the scenario described in the above Note, and to safely upgrade vWAAS memory and disk for Akamai Connect for the Cisco vWAAS-12000, use the following procedure:

Procedure

Step 1 Power off the vWAAS VM.

Step 2 Add an additional disk of the required size for your system.

Step 3 Increase the size of the RAM.

Note To run Akamai Connect on vWAAS-12000, you must increase the size of the RAM by at least 6 GB.

Step 4 Increase the size of the `kdump` file from 12.2 GB to 19 GB.

To enable the kernel crash dump mechanism, use the `kernel kdump enable global` configuration command. To display kernel crash dump information for the device, use the `show kdump EXEC` command.

Step 5 Power on the Cisco vWAAS VM.

Step 6 Check the alarms.

The `filesystem_size_mism` alarm will be raised:

```
Critical Alarms
-----
```

Alarm ID	Module/Submodule	Instance
1 filesystem_size_mism	disk	Filesystem size

Step 7 Run the `disk delete-data-partitions` command.

Note The **disk delete-data-partitions** command deletes the cache files, including the DRE cache files.

Step 8 Reload the device.

- After running the **disk delete-data-partitions** command, you must reload the device.

The reload process automatically re-creates data partitions, and initializes the caches. This process may take several minutes.

DRE optimization will not start until the DRE cache has finished initializing.

Cisco vWAAS-150 with Akamai Connect

Consider the following guidelines for Cisco vWAAS-150 with Akamai Connect:

- For Cisco vWAAS in WAAS Version 6.1.1 and later, Cisco vWAAS-150 on Cisco ISR-WAAS is supported for Akamai Connect. For Cisco vWAAS in WAAS Version 6.2.1 and later, vWAAS-150 is also supported for RHEL KVM and Microsoft Hyper-V.

Downgrading Cisco vWAAS-150 for RHEL KVM or for Microsoft Hyper-v to a version earlier than vWAAS in Cisco WAAS Version 6.2.1 is *not* supported.

- For the Cisco vWAAS-150 model, the Cisco WAAS Central Manager *must* be Cisco WAAS Version 6.2.1 or later, but the mixed versions of device models (Cisco WAAS Version 6.2.1 and earlier) are also supported. The Cisco WAAS Central Manager must be a version that is equal to or later than the associated devices.

Cisco vWAAS-150 is deployed *only* in Cisco WAAS Version 6.1.1 and later. Therefore, you cannot upgrade or downgrade Cisco vWAAS-150 from Cisco WAAS Version 6.1.1.

The following table shows specifications for vWAAS-150.

Table 5: Cisco vWAAS-150 Profile

Feature	Description
Memory with Akamai Connect	4 GB
Disk with Akamai Connect	160 GB
vCPU	1 vCPU
Module	Cisco UCS E-Series NCE blade (PID: UCS-EN120E-208-M2/K9), supported on Cisco ISR-G2 platform
NIM Module	Cisco UCS E-Series NCE NIM blade (PID: UCS-EN140N-M2/K9), supported on Cisco ISR-G3 platform

Akamai Connect Cache Engine on Cisco Mid-End and High-End Platforms

In Cisco WAAS Version 6.2.1 and later, the Akamai Connect Cache Engine is supported for scaling beyond 6,000 Cisco vWAAS connections on the following platforms:

- Cisco WAVE-7541, Cisco WAVE-7571, and Cisco WAVE-8541
- Cisco vWAAS-12000 and Cisco vWAAS-50000

Scaling for these platforms is based on memory availability, scale performance, and the particular dynamic cache size management feature. The table "Cisco WAAS Mid to High End Platform Cache Engine Memory Requirements" shows the connections, total memory, and cache engine memory requirements for each of these platforms. The table "Cisco WAAS Mid to High End Platform Cache Engine Cache Disk Requirements" shows the connections, number of disks, and cache engine disks for each of these platforms.

The Akamai Connect cache engine connection-handling capacity is determined by the upper limit of memory that is given to the Akamai Connect cache engine at startup. The Akamai Connect cache engine allocates memory, as needed, up to the upper limit; on approaching that limit, it pushes back new connections. In case of overload, the connection is optimized by HTTP-AO, without caching benefit.

For Cisco vWAAS-12000 and Cisco vWAAS-50000, HTTP object cache will scale up to the platform TFO limit. To achieve this, augment the platform resources (CPU, RAM, and disk) during provisioning:

- For vWAAS-12000, allocate at least 6 GB of additional RAM.
- For vWAAS-12000 and vWAAS-50000, allocate cache engine cache disk resources. Cache disk requirements are shown in the table "Cisco WAAS Mid to High End Platform Cache Engine Cache Disk Requirements".

Table 6: Cisco WAAS Mid to High End Platform Cache Engine Memory Requirements

Cisco WAAS Platform	HTTP Object Cache Connections	CPU	Total Memory	Memory Required for Cache Engine
vWAAS-12000	12 K	4	18 GB	4308 M
vWAAS-50000	50 K	8	48 GB	14136 M
WAVE-7541	18 K	2	24 GB	5802 M
WAVE-7571	60 K/ 50 K/ 40 K	2	48 GB	15360 M or 14125 M or 11565 M
WAVE-8541	150 K/ 125 K/ 100 K	2	96 GB	38400 M or 32000 M or 25600 M

Table 7: Cisco WAAS Mid to High End Platform Cache Engine Cache Disk Requirements

Cisco WAAS Platform	HTTP Object Cache Connections	CPU	Disk/ CE Cache Disk	Cache Engine Cache Disk
vWAAS-12000	12 K	4	750 GB	750 GB

Cisco WAAS Platform	HTTP Object Cache Connections	CPU	Disk/ CE Cache Disk	Cache Engine Cache Disk
vWAAS-50000	50 K	8	1500 GB	850 GB
WAVE-7541	18 K	2	2200 GB	708 GB
WAVE-7571	60 K/ 50 K/ 40 K	2	3100 GB	839 GB
WAVE-8541	150 K/ 125 K/100 K	2	4.1 TB	675 GB

