



H.323 RAS Support

This feature introduces support for H.225 Registration, Admission, and Status (RAS) signaling in zone-based firewalls. RAS is a signaling protocol that is used between endpoints (such as gateways) and gatekeepers.

The H.225 standard is used by H.323 for call setup. H.255 includes RAS control, which is used to communicate with the gatekeeper. A RAS signaling channel enables connections between the gatekeeper and H.323 endpoints.

- [Finding Feature Information, page 1](#)
- [Restrictions for H.323 RAS Support, page 1](#)
- [How to Configure H.323 RAS Support, page 2](#)
- [Configuration Examples for H.323 RAS Support, page 5](#)
- [Additional References for H.323 RAS Support, page 6](#)
- [Feature Information for H.323 RAS Support, page 7](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for H.323 RAS Support

H.225 RAS inspection is supported only with zone-based policy firewall inspection.

How to Configure H.323 RAS Support

Configuring a Class Map for H.323 RAS Protocol Inspection

Use this task to configure a class map for classifying network traffic.

SUMMARY STEPS

1. `enable`
2. `configure terminal`
3. `class-map type inspect [match-any | match-all] class-map-name`
4. `match access-group {access-group | name access-group-name}`
5. `match protocol protocol-name [signature]`
6. `match protocol protocol-name [signature]`
7. `match class-map class-map-name`
8. `exit`

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	class-map type inspect [match-any match-all] class-map-name Example: Router(config)# class-map type inspect match-all c1	Creates a Layer 3 or Layer 4 inspect type class map and enters class-map configuration mode.
Step 4	match access-group {access-group name access-group-name} Example: Router(config-cmap)# match access-group 101	(Optional) Configures the match criterion for a class map based on the access control list (ACL) name or number.

	Command or Action	Purpose
Step 5	match protocol <i>protocol-name</i> [signature] Example: <pre>Router(config-cmap)# match protocol h225ras</pre>	Configures the match criterion for a class map on the basis of a specified protocol. Note You should specify the h225ras keyword to create a class-map for H.225 RAS protocol classification. For a list of supported protocols, use the command-line interface (CLI) help option (?) on your platform.
Step 6	match protocol <i>protocol-name</i> [signature] Example: <pre>Router(config-cmap)# match protocol h323</pre>	Configures the match criterion for a class map on the basis of a specified protocol. Note You should specify the h323 keyword to create a class-map for H.323 protocol classification.
Step 7	match class-map <i>class-map-name</i> Example: <pre>Router(config-cmap)# match class-map c1</pre>	(Optional) Specifies a previously defined class as the match criterion for a class map.
Step 8	exit Example: <pre>Router(config-cmap)# exit</pre>	Returns to global configuration mode.

Creating a Policy Map for H.323 RAS Protocol Inspection

Use this task to create a policy map for a firewall policy that will be attached to zone pairs.



Note If you are creating an inspect type policy map, only the following actions are allowed: drop, inspect, police, and pass.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **policy-map type inspect** *policy-map-name*
4. **class type inspect** *class-name*
5. **inspect** [*parameter-map-name*]
6. **police rate** bps burst size
7. **drop** [log]
8. **pass**
9. **exit**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	policy-map type inspect <i>policy-map-name</i> Example: Router(config)# policy-map type inspect pl	Creates a Layer 3 and Layer 4 inspect type policy map and enters policy-map configuration mode.
Step 4	class type inspect <i>class-name</i> Example: Router(config-pmap)# class type inspect cl	Specifies the traffic (class) on which an action is to be performed and enters policy-map class configuration mode.
Step 5	inspect [<i>parameter-map-name</i>] Example: Router(config-pmap-c)# inspect inspect-params	Enables Cisco IOS stateful packet inspection.

	Command or Action	Purpose
Step 6	<p>police rate bps burst size</p> <p>Example:</p> <pre>Router(config-pmap-c)# police rate 2000 burst 3000</pre>	(Optional) Limits traffic matching within a firewall (inspect) policy.
Step 7	<p>drop [log]</p> <p>Example:</p> <pre>Router(config-pmap-c)# drop</pre>	<p>(Optional) Drops packets that are matched with the defined class.</p> <p>Note The actions drop and pass are exclusive, and the actions inspect and drop are exclusive; that is, you cannot specify both of them.</p>
Step 8	<p>pass</p> <p>Example:</p> <pre>Router(config-pmap-c)# pass</pre>	(Optional) Allows packets that are matched with the defined class.
Step 9	<p>exit</p> <p>Example:</p> <pre>Router(config-pmap-c)# exit</pre>	Returns to policy-map configuration mode.

What to Do Next

After configuring an H.323 RAS protocol firewall policy, you want to attach the policy to a zone pair. For information on completing this task, see the “Zone-Based Policy Firewall” module.

Configuration Examples for H.323 RAS Support

Example H.323 RAS Protocol Inspection Configuration

The following example shows how to configure an H.323 RAS protocol inspection policy:

```
class-map type inspect match-any c1
  match protocol h323
  match protocol h225ras
class-map type inspect match-all c2
  match protocol icmp
!
policy-map type inspect p1
  class type inspect c1
  inspect
  class class-default
  drop
```

```

policy-map type inspect p2
  class type inspect c2
  inspect
  class class-default
  drop
!
zone security z1
  description One-Network zone
zone security z2
  description Two-Network zone
zone-pair security zp source z1 destination z2
  service-policy type inspect p1
zone-pair security zp-rev source z2 destination z1
  service-policy type inspect p2
!
interface FastEthernet1/0
  ip address 10.0.0.0 255.255.0.0
  zone-member security z1
  duplex auto
  speed auto
!
interface FastEthernet1/1
  ip address 10.0.1.1 255.255.0.0
  zone-member security z2
  duplex auto
  speed auto

```

Example H.225 RAS Firewall Policy Configuration

The following example shows how to configure the firewall policy to inspect H.225 RAS messages:

```

interface GigabitEthernet 0/1/5
  ip address 172.16.0.0 255.255.0.0
  zone-member security private
  no shut
!
interface GigabitEthernet 0/1/6
  ip address 192.168.0.0 255.255.0.0
  zone-member security internet
  no shut
!
zone security private
zone security internet
!
class-map type inspect match-any internet-traffic-class
  match protocol h225ras
  match protocol h323
!
policy-map type inspect private-internet-policy
  class type inspect internet-traffic-class
  inspect
  class class-default
!
zone-pair security private-internet source private destination internet
  service-policy type inspect private-internet-policy

```

Additional References for H.323 RAS Support

Related Documents

Related Topic	Document Title
Cisco IOS commands	Master Commands List, All Releases

Related Topic	Document Title
Firewall commands	<ul style="list-style-type: none"> • Security Command Reference: Commands A to C • Security Command Reference: Commands D to L • Security Command Reference: Commands M to R • Security Command Reference: Commands S to Z

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for H.323 RAS Support

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 1: Feature Information for H.323 RAS Support

Feature Name	Releases	Feature Information
H.323 RAS Support	12.4(11)T	<p>H.323 RAS Support feature introduces support for H.255 Registration, Admission, and Status (RAS) signaling in zone-based firewalls.</p> <p>The following command was introduced or modified: match protocol (zone).</p>

