

# マルチキャスト ルーティング - MSDP と PIM のウォークスルー

## 内容

[概要](#)

[トポロジ](#)

[コントロールプレーン](#)

[送信元の登録 \(ステップ 1 ~ 3\)](#)

[レシーバ参加グループ \(ステップ4 ~ 11\)](#)

[R4 PIM RPプルーニングオフ\(S,G\)ステップ12](#)

[要約](#)

[関連情報](#)

## 概要

このドキュメントでは、単純なマルチキャストトポロジを使用したProtocol Independent Multicast(PIM)およびMulticast Source Discovery Protocol(MSDP)の動作について説明します。これは、送信元が登録されたときから受信側がマルチキャストパケットを受信し始めるまでの、コントロールプレーンの動作とイベントのシーケンスを理解するのに役立ちます。

注：このドキュメントで使用するデバイスは、ラボ環境でCisco IOS®バージョン15.3Mを実行します。

## トポロジ

左側の自律システム AS65000 には、マルチキャスト ソースが含まれます。R1はファーストホップルータ(FHR)として機能し、送信元(10.1.1.1)をPIMランデブーポイント(PIM RP)R3に登録します。R7とR3はiBGPネイバーで、R3-R4とR7-R6はeBGPネイバーです。R7 と R6 は 2 つの自律システム間の優先パスとして設定されます。AS64999では、R5にローカルに接続されたレシーバがあります。R5 は PIM RP として R4 を使用するように設定されます。

## コントロールプレーン

このビデオは、どのメッセージがいつ送信されるかを示しています。各ステップの詳細な説明については、このビデオと読み上げをご覧ください。

### 送信元の登録 (ステップ 1 ~ 3)

送信元は239.1.1.1へのマルチキャストデータの送信を開始します。このデータを受信すると、R1(セグメントのPIM指定ルータ(DR)である)がマルチキャストパケットを取得し、PIMレジスタメッセージを作成します。

レジスタメッセージは、送信元をPIM RPに通知するためにR1からR3に送信されるユニキャスト

PIM/パケットです。

```
R1#
*May 21 14:54:08.461: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:54:08.461: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
*May 21 14:54:08.461: PIM(0): Adding register encap tunnel (Tunnel0) as forwarding
interface of (10.1.1.1, 239.1.1.1).
```

ここで、PIM RP、R3はレジスタメッセージを受信し、register-stopで応答します。R3 はまた、MSDP SA メッセージを MSDP 経由で R4 に送信します。 mrouteの「A」フラグは、MSDPアドバタイズメントの候補であることを意味します。「P」フラグは、そのグループに対して受信側または発信インターフェイスがないため、プルーニングされたことを示します。

```
R3#
*May 21 14:54:08.459: PIM(0): Received v2 Register on Ethernet1/0 from 10.0.12.1
*May 21 14:54:08.459:           for 10.1.1.1, group 239.1.1.1
*May 21 14:54:08.459: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:54:08.459: PIM(0): Adding register decap tunnel (Tunnel1) as accepting
interface of (*, 239.1.1.1).
*May 21 14:54:08.459: PIM(0): Adding register decap tunnel (Tunnel1) as accepting
interface of (10.1.1.1, 239.1.1.1).
*May 21 14:54:08.459: PIM(0): Send v2 Register-Stop to 10.0.12.1 for 10.1.1.1,
group 239.1.1.1
```

```
R3#show ip mroute 239.1.1.1
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode

(*, 239.1.1.1), 00:00:33/stopped, RP 10.10.10.10, flags: SP
  Incoming interface: Null, RPF nbr 0.0.0.0
  Outgoing interface list: Null

(10.1.1.1, 239.1.1.1), 00:00:33/00:02:26, flags: PA
  Incoming interface: Ethernet1/0, RPF nbr 10.0.37.7
  Outgoing interface list: Null
```

```
R3#show ip msdp sa-cache
MSDP Source-Active Cache - 0 entries
R3#
*May 21 14:54:58.511: MSDP(0): (10.1.1.1/32, 239.1.1.1)
```

ここで、R1はR3からregister-stopを受信します。

```
*May 21 14:54:08.461: PIM(0): Received v2 Register-Stop on Ethernet0/0 from 10.10.10.10
*May 21 14:54:08.461: PIM(0):   for source 10.1.1.1, group 239.1.1.1
*May 21 14:54:08.461: PIM(0): Removing register encap tunnel (Tunnel0) as forwarding
interface of (10.1.1.1, 239.1.1.1).
*May 21 14:54:08.461: PIM(0): Clear Registering flag to 10.10.10.10 for
(10.1.1.1/32, 239.1.1.1)
```

R4では、mroute状態はありませんが、MSDP SAがあります。

```
R4#show ip mroute
```

```
*May 21 14:54:58.591: MSDP(0): (10.1.1.1/32, 239.1.1.1), accepted
```

```
R4#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 224.0.1.40), 00:35:32/00:02:31, RP 10.20.20.20, flags: SJCL
```

```
Incoming interface: Null, RPF nbr 0.0.0.0
```

```
Outgoing interface list:
```

```
Ethernet1/0, Forward/Sparse, 00:23:16/00:02:36
```

```
Loopback0, Forward/Sparse, 00:35:31/00:02:31
```

```
R4#show ip msdp sa-cache
```

```
MSDP Source-Active Cache - 1 entries
```

```
(10.1.1.1, 239.1.1.1), RP 10.10.10.10, BGP/AS 65000, 00:01:00/00:05:49, Peer 10.33.33.33
```

## レシーバ参加グループ ( ステップ4 ~ 11 )

R5はインターフェイスでIGMP joinを受信し、PIM joinパケット(\*,G join)を構築します。この参加は R6 に送信されます。

```
R5#conf t
```

```
Enter configuration commands, one per line.  End with CNTL/Z.
```

```
R5(config)#int e0/1
```

```
R5(config-if)#ip igmp join-group 239.1.1.1
```

```
R5(config-if)#
```

```
*May 21 14:56:43.234: PIM(0): Check RP 10.20.20.20 into the (*, 239.1.1.1) entry
```

```
*May 21 14:56:43.234: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
```

```
*May 21 14:56:43.234: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
```

```
*May 21 14:56:43.234: PIM(0): Insert (*,239.1.1.1) join in nbr 10.0.56.6's queue
```

```
*May 21 14:56:43.246: PIM(0): Building Join/Prune packet for nbr 10.0.56.6
```

```
*May 21 14:56:43.246: PIM(0): Adding v2 (10.20.20.20/32, 239.1.1.1), WC-bit, RPT-bit,
S-bit Join
```

```
*May 21 14:56:43.246: PIM(0): Send v2 join/prune to 10.0.56.6 (Ethernet0/0)
```

R6 は R5 から ( \*,G ) PIM 参加を受信し、 ( \*,G ) 参加を R4 PIM RP に送信します。

```
R6#
*May 21 14:56:43.248: PIM(0): Received v2 Join/Prune on Ethernet2/0 from 10.0.56.5,
to us
*May 21 14:56:43.248: PIM(0): Join-list: (*, 239.1.1.1), RPT-bit set, WC-bit set,
S-bit set
*May 21 14:56:43.248: PIM(0): Check RP 10.20.20.20 into the (*, 239.1.1.1) entry
*May 21 14:56:43.248: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune
message for 239.1.1.1
*May 21 14:56:43.248: PIM(0): Add Ethernet2/0/10.0.56.5 to (*, 239.1.1.1), Forward
state, by PIM *G Join
*May 21 14:56:43.248: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune
message for 239.1.1.1
*May 21 14:56:43.248: PIM(0): Insert (*,239.1.1.1) join in nbr 10.0.46.4's queue
*May 21 14:56:43.248: PIM(0): Building Join/Prune packet for nbr 10.0.46.4
*May 21 14:56:43.248: PIM(0): Adding v2 (10.20.20.20/32, 239.1.1.1), WC-bit,
RPT-bit, S-bit Join
*May 21 14:56:43.248: PIM(0): Send v2 join/prune to 10.0.46.4 (Ethernet1/0)
```

R4 PIM RPはR6から(\*,G)参加を受信し、次に(S,G)参加を送信元10.1.1.1に向けて送信し、R6に戻ります。

```
R4#
*May 21 14:56:43.331: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.6,
to us
*May 21 14:56:43.331: PIM(0): Join-list: (*, 239.1.1.1), RPT-bit set, WC-bit set,
S-bit set
*May 21 14:56:43.331: PIM(0): Check RP 10.20.20.20 into the (*, 239.1.1.1) entry
*May 21 14:56:43.331: PIM(0): Adding register decap tunnel (Tunnell) as accepting
interface of (*, 239.1.1.1).
*May 21 14:56:43.331: PIM(0): Add Ethernet1/0/10.0.46.6 to (*, 239.1.1.1), Forward
state, by PIM *G Join
*May 21 14:56:43.331: PIM(0): Adding register decap tunnel (Tunnell) as accepting
interface of (10.1.1.1, 239.1.1.1).
*May 21 14:56:43.331: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.46.6's queue
R4#
*May 21 14:56:43.331: PIM(0): Building Join/Prune packet for nbr 10.0.46.6
*May 21 14:56:43.331: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.331: PIM(0): Send v2 join/prune to 10.0.46.6 (Ethernet1/0)
```

R6 は R4 から ( S,G ) 参加を受信し、 ( S,G ) 参加を AS65000 の R7 に送信します。 R4 から ( S,G ) 参加を受信したら、R6 は ( SGR ) プルーニングを R4 に送信します ( ステップ 9 )。これは、R4 での重複パケットを避けるために行われます。

```
*May 21 14:56:43.248: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4,
to us
*May 21 14:56:43.248: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.248: PIM(0): Add Ethernet1/0/10.0.46.4 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
*May 21 14:56:43.248: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.67.7's queue
R6#
*May 21 14:56:43.248: PIM(0): Building Join/Prune packet for nbr 10.0.67.7
*May 21 14:56:43.248: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.248: PIM(0): Send v2 join/prune to 10.0.67.7 (Ethernet0/0)
R6#
*May 21 14:56:44.476: PIM(0): Insert (10.1.1.1,239.1.1.1) sgr prune in nbr 10.0.46.4's
queue
*May 21 14:56:44.476: PIM(0): Building Join/Prune packet for nbr 10.0.46.4
*May 21 14:56:44.476: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), RPT-bit, S-bit Prune
```

\*May 21 14:56:44.476: PIM(0): Send v2 join/prune to 10.0.46.4 (Ethernet1/0)

R7はR6から(S,G)参加を受信し、次に送信元へのルートに従い、(S,G)参加をR2に送信します。

R7#

```
*May 21 14:56:43.241: PIM(0): Received v2 Join/Prune on Ethernet0/0 from 10.0.67.6,
to us
*May 21 14:56:43.241: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.241: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:56:43.241: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune message
for 239.1.1.1
*May 21 14:56:43.241: PIM(0): Add Ethernet0/0/10.0.67.6 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
*May 21 14:56:43.241: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.27.2's queue
*May 21 14:56:43.241: PIM(0): Building Join/Prune packet for nbr 10.0.27.2
```

R7#

```
*May 21 14:56:43.241: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.241: PIM(0): Send v2 join/prune to 10.0.27.2 (Ethernet2/0)
```

R7#show ip mroute

IP Multicast Routing Table

Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,  
L - Local, P - Pruned, R - RP-bit set, F - Register flag,  
T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,  
X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,  
U - URD, I - Received Source Specific Host Report,  
Z - Multicast Tunnel, z - MDT-data group sender,  
Y - Joined MDT-data group, y - Sending to MDT-data group,  
G - Received BGP C-Mroute, g - Sent BGP C-Mroute,  
Q - Received BGP S-A Route, q - Sent BGP S-A Route,  
V - RD & Vector, v - Vector

Outgoing interface flags: H - Hardware switched, A - Assert winner

Timers: Uptime/Expires

Interface state: Interface, Next-Hop or VCD, State/Mode

(\* , 239.1.1.1), 00:03:33/stopped, RP 10.10.10.10, flags: SP

Incoming interface: Ethernet1/0, RPF nbr 10.0.37.3

Outgoing interface list: Null

(10.1.1.1, 239.1.1.1), 00:03:33/00:02:56, flags: T

Incoming interface: Ethernet2/0, RPF nbr 10.0.27.2

Outgoing interface list:

Ethernet0/0, Forward/Sparse, 00:03:33/00:02:53

R2はR7から(S,G)参加を受信し、次に送信元へのルートに従い、(S,G)参加をR1に送信します

R2#

```
*May 21 14:56:43.253: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.27.7,
to us
*May 21 14:56:43.253: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.253: PIM(0): Check RP 10.10.10.10 into the (*, 239.1.1.1) entry
*May 21 14:56:43.253: PIM(0): Building Triggered (*,G) Join / (S,G,RP-bit) Prune
message for 239.1.1.1
*May 21 14:56:43.253: PIM(0): Add Ethernet1/0/10.0.27.7 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
*May 21 14:56:43.253: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.12.1's queue
*May 21 14:56:43.253: PIM(0): Building Join/Prune packet for nbr 10.0.12.1
```

R2#

```
*May 21 14:56:43.253: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:43.253: PIM(0): Send v2 join/prune to 10.0.12.1 (Ethernet0/0)
```

```
R2#show ip mroute
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:01:27/stopped, RP 10.10.10.10, flags: SP
Incoming interface: Ethernet1/0, RPF nbr 10.0.27.7
Outgoing interface list: Null
```

```
(10.1.1.1, 239.1.1.1), 00:01:27/00:01:32, flags: T
Incoming interface: Ethernet0/0, RPF nbr 10.0.12.1
Outgoing interface list:
```

```
  Ethernet1/0, Forward/Sparse, 00:01:27/00:03:01
```

**R1はR2から(S,G)参加を受信し、発信インターフェイスリストにインターフェイスを追加します**

```
*May 21 14:56:43.261: PIM(0): Received v2 Join/Prune on Ethernet0/0 from 10.0.12.2,
to us
*May 21 14:56:43.261: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
*May 21 14:56:43.261: PIM(0): Add Ethernet0/0/10.0.12.2 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
```

```
R1#show ip mroute
IP Multicast Routing Table
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
       L - Local, P - Pruned, R - RP-bit set, F - Register flag,
       T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
       X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
       U - URD, I - Received Source Specific Host Report,
       Z - Multicast Tunnel, z - MDT-data group sender,
       Y - Joined MDT-data group, y - Sending to MDT-data group,
       G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
       Q - Received BGP S-A Route, q - Sent BGP S-A Route,
       V - RD & Vector, v - Vector
Outgoing interface flags: H - Hardware switched, A - Assert winner
Timers: Uptime/Expires
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:03:25/stopped, RP 10.10.10.10, flags: SPF
Incoming interface: Ethernet0/0, RPF nbr 10.0.12.2
Outgoing interface list: Null
```

```
(10.1.1.1, 239.1.1.1), 00:03:25/00:03:24, flags: FT
Incoming interface: Ethernet0/1, RPF nbr 0.0.0.0
Outgoing interface list:
```

```
  Ethernet0/0, Forward/Sparse, 00:00:50/00:02:39
```

**この時点で、データは送信元から受信側まで流れます。データパケットを受信すると、R5は(\*,G)ツリーから(S,G)ツリーにスイッチします。**

```
R5#
*May 21 14:56:44.494: PIM(0): Insert (10.1.1.1,239.1.1.1) join in nbr 10.0.56.6's queue
*May 21 14:56:44.498: PIM(0): Building Join/Prune packet for nbr 10.0.56.6
*May 21 14:56:44.498: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Join
*May 21 14:56:44.498: PIM(0): Send v2 join/prune to 10.0.56.6 (Ethernet0/0)
```

```
R5#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
      L - Local, P - Pruned, R - RP-bit set, F - Register flag,
      T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
      X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
      U - URD, I - Received Source Specific Host Report,
      Z - Multicast Tunnel, z - MDT-data group sender,
      Y - Joined MDT-data group, y - Sending to MDT-data group,
      G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
      Q - Received BGP S-A Route, q - Sent BGP S-A Route,
      V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:02:47/stopped, RP 10.20.20.20, flags: SJCL
```

```
Incoming interface: Ethernet0/0, RPF nbr 10.0.56.6
```

```
Outgoing interface list:
```

```
Ethernet0/1, Forward/Sparse, 00:02:47/00:02:14
```

```
(10.1.1.1, 239.1.1.1), 00:02:45/00:00:14, flags: LJT
```

```
Incoming interface: Ethernet0/0, RPF nbr 10.0.56.6
```

```
Outgoing interface list:
```

```
Ethernet0/1, Forward/Sparse, 00:02:45/00:02:14
```

R6はR5から(S,G)参加を受信し、データパケットをE2/0からR5に送信します。

```
R6#
```

```
*May 21 14:56:44.496: PIM(0): Received v2 Join/Prune on Ethernet2/0 from 10.0.56.5,
to us
```

```
*May 21 14:56:44.496: PIM(0): Join-list: (10.1.1.1/32, 239.1.1.1), S-bit set
```

```
*May 21 14:56:44.496: PIM(0): Update Ethernet2/0/10.0.56.5 to (10.1.1.1, 239.1.1.1),
Forward state, by PIM SG Join
```

```
*May 21 14:56:49.056: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4,
to us
```

```
*May 21 14:56:49.056: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1)
```

```
*May 21 14:56:49.056: PIM(0): Prune Ethernet1/0/239.1.1.1 from (10.1.1.1/32, 239.1.1.1)
- deleted
```

```
R6#show ip mroute
```

```
IP Multicast Routing Table
```

```
Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,
      L - Local, P - Pruned, R - RP-bit set, F - Register flag,
      T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,
      X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,
      U - URD, I - Received Source Specific Host Report,
      Z - Multicast Tunnel, z - MDT-data group sender,
      Y - Joined MDT-data group, y - Sending to MDT-data group,
      G - Received BGP C-Mroute, g - Sent BGP C-Mroute,
      Q - Received BGP S-A Route, q - Sent BGP S-A Route,
      V - RD & Vector, v - Vector
```

```
Outgoing interface flags: H - Hardware switched, A - Assert winner
```

```
Timers: Uptime/Expires
```

```
Interface state: Interface, Next-Hop or VCD, State/Mode
```

```
(* , 239.1.1.1), 00:03:43/00:02:42, RP 10.20.20.20, flags: S
Incoming interface: Ethernet1/0, RPF nbr 10.0.46.4
Outgoing interface list:
Ethernet2/0, Forward/Sparse, 00:03:43/00:02:42
```

```
(10.1.1.1, 239.1.1.1), 00:03:43/00:02:46, flags: T
Incoming interface: Ethernet0/0, RPF nbr 10.0.67.7
Outgoing interface list:
Ethernet2/0, Forward/Sparse, 00:03:43/00:02:44
```

## R4 PIM RPルーニングオフ(S,G)ステップ12

最後に、R4 PIM RPが(S,G)ルーニングをR6に送信します。 mroute ( MSDP が作成したエントリ ) に「M」フラグがあることに注意してください。

R4#

```
*May 21 14:56:44.559: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.6,
to us
```

```
*May 21 14:56:44.559: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1) RPT-bit set
```

```
*May 21 14:56:44.579: PIM(0): Removing register decap tunnel (Tunnell) as accepting
interface of (10.1.1.1, 239.1.1.1).
```

```
*May 21 14:56:44.579: PIM(0): Installing Ethernet1/0 as accepting interface for
(10.1.1.1, 239.1.1.1).
```

```
*May 21 14:56:46.107: MSDP(0): (10.1.1.1/32, 239.1.1.1), accepted
```

```
*May 21 14:56:49.139: PIM(0): Insert (10.1.1.1,239.1.1.1) prune in nbr 10.0.46.6's queue
```

```
*May 21 14:56:49.139: PIM(0): Building Join/Prune packet for nbr 10.0.46.6
```

```
*May 21 14:56:49.139: PIM(0): Adding v2 (10.1.1.1/32, 239.1.1.1), S-bit Prune
```

```
*May 21 14:56:49.139: PIM(0): Send v2 join/prune to 10.0.46.6 (Ethernet1/0)
```

R4#show ip mroute

IP Multicast Routing Table

Flags: D - Dense, S - Sparse, B - Bidir Group, s - SSM Group, C - Connected,

L - Local, P - Pruned, R - RP-bit set, F - Register flag,

T - SPT-bit set, J - Join SPT, M - MSDP created entry, E - Extranet,

X - Proxy Join Timer Running, A - Candidate for MSDP Advertisement,

U - URD, I - Received Source Specific Host Report,

Z - Multicast Tunnel, z - MDT-data group sender,

Y - Joined MDT-data group, y - Sending to MDT-data group,

G - Received BGP C-Mroute, g - Sent BGP C-Mroute,

Q - Received BGP S-A Route, q - Sent BGP S-A Route,

V - RD & Vector, v - Vector

Outgoing interface flags: H - Hardware switched, A - Assert winner

Timers: Uptime/Expires

Interface state: Interface, Next-Hop or VCD, State/Mode

```
(* , 239.1.1.1), 00:02:15/00:03:12, RP 10.20.20.20, flags: S
```

```
Incoming interface: Null, RPF nbr 0.0.0.0
```

```
Outgoing interface list:
```

```
Ethernet1/0, Forward/Sparse, 00:02:15/00:03:12
```

```
(10.1.1.1, 239.1.1.1), 00:02:15/00:02:46, flags: PMT
```

```
Incoming interface: Ethernet1/0, RPF nbr 10.0.46.6
```

```
Outgoing interface list: Null
```

ここでは、発信インターフェイス(OIF)E1/0からR4がR6から削除されます。

R6#

```
*May 21 14:56:49.056: PIM(0): Received v2 Join/Prune on Ethernet1/0 from 10.0.46.4,to us
```



```
*May 21 14:56:49.056: PIM(0): Prune-list: (10.1.1.1/32, 239.1.1.1)
*May 21 14:56:49.056: PIM(0): Prune Ethernet1/0/239.1.1.1 from (10.1.1.1/32, 239.1.1.1)
- deleted
R6#
```

## 要約

MSDP はそれぞれ独自の RP を使用し、異なる PIM ドメインの相互接続方法を提供します。またこれは「エニーキャスト RP」を実装するためにもよく使用されますが、このドキュメントの範囲外です。MSDP と PIM が連携し、あるドメインのレシーバが別のドメインのソースからのトラフィックを受信できるようにします。MSDP SA メッセージにより、他の RP が他の PIM ドメインのソースについて学ぶことができ、PIM はマルチキャスト ツリーを構築するために使用されます。

プロトコルの動作の詳細については、関連情報に記載されているRFCを参照してください。

## 関連情報

- PIM RFC

<https://tools.ietf.org/html/rfc4601>

- MSDP RFC

<https://tools.ietf.org/html/rfc3618>