

Probleemoplossing voor CVP Call Flow Analysis met VB Server

Inhoud

[Inleiding](#)

[Voorwaarden](#)

[Vereisten](#)

[Gebruikte componenten](#)

[Achtergrondinformatie](#)

[CVP met VB Call Flow Analyse](#)

[Gerelateerde informatie](#)

Inleiding

Dit document beschrijft spooranalyse van Cisco Customer Voice Portal (CVP) met Cisco Virtual Voice browser (VVB) als een VXML-browser.

Voorwaarden

Vereisten

Cisco raadt kennis van de volgende onderwerpen aan:

- CVP met Cisco Unified Contact Center Enterprise (UCCE)
- Cisco VVB geïntegreerd in CVP
- CVP uitgebreide Call Flow

Gebruikte componenten

De informatie in dit document is gebaseerd op de volgende software- en hardware-versies:

- CVP 11,5
- UCS E11.5
- VVB 11,5

De informatie in dit document is gebaseerd op de apparaten in een specifieke laboratoriumomgeving. Alle apparaten die in dit document worden beschreven, hadden een opgeschoonde (standaard)configuratie. Als uw netwerk levend is, zorg er dan voor dat u de mogelijke impact van om het even welke opdracht begrijpt.

Achtergrondinformatie

Met de introductie van Cisco VVB als VXML browser, hier is een voorbeeldsporenanalyse om signalen tussen CVP, UCCE en VVB te volgen.

In deze analyse wordt de oproep naar de CVP gestuurd en na behandeling met Interactive Voice Respose (IVR) leidt CVP de oproep naar een beschikbare agent.

CVP- en VVB-lognippen kunnen worden geïdentificeerd met behulp van MIVR- en CVP-sleutelwoorden in de sporen.

CVP met VB Call Flow Analyse

Nieuw gespreksstadium

```
1937: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=DATAI.1} NEW CALL with guid=0F46E580000100000000007A0851430A legid=56A1AA52-345511E7-ABF1C227-5C85A942 dn=9876 ani=12345 uui=null calldate=Wed May 10 11:39:37 EST 2017 video=false cachecallcontext = false is_postcallsurvey = false RouterCallKey = null RouterCallKeyDay = null RouterCallKeySequenceNumber = null
```

Aantal actieve sessies

```
44241: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Core-router-group-0} --NEW SESSION CREATED--CALLGUID=0F46E580000100000000007A0851430A NUMBER OF ACTIVE SESSIONS= 1
```

Nieuwe oproep op SIP SS

```
4281: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from SIP_SS - [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=9876 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0 serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables= ECC arrays= Peripheral Variables=
```

New CALL-publicatie naar UCCE

```
4282: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Publishing to UCCE - [NEW_CALL] DialogID=46 SendSeqNo=1 DNIS=9876 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=100 trunkNumber=0 serviceId=1 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables=user.media.id: 0F46E580000100000000007A0851430A, ECC arrays= Peripheral Variables=
```

Tijdelijke conforme verwerking van UCCE

```
4283: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from UCCE - ,, [ICM_TEMPORARY_CONNECT], rckey=201, rcdays=152070, DNIS=9876, ANI=12345
```

Tijdelijke verbinding-publicatie naar stap SS

```
4284: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-
group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] -
Publishing to SIP_SS - [CONNECT] DialogID=46 SendSeqNo=0 Label=8888111111 TxrHint=false
rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce=null
callguid=0F46E580000100000000007A0851430A ECC variables=user.media.id:
0F46E580000100000000007A0851430A,user.microapp.app_media_lib: ..,user.microapp.media_server:
http://192.0.2.11:7000/CVP,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=
```

Routeaanpassing voor VRU-label

```
1941: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} Static route matched 88881111112 to StaticRoute: patterns like 8888111111> will route
to 192.0.2.12
1942: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} Using Local Static Route for sip:88881111112@192.0.2.12
```

Uitnodigen tot VXML GW-VRU Been

```
1947: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-
149438037789633 - [OUTBOUND]: INVITE TO <sip:88881111112@192.0.2.12;transport=tcp> FROM "PSTN
PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[60] 100REL[Unsupported]
```

Nieuwe oproep aan VB VRU-been

```
195208: May 10 11:21:27.305 AEST %MIVR-JASMIN-7-UNK:[CALLID=0F46E580000100000000007A0851430A-
149438037789633] NEW_CALL, GUCID=0F46E580000100000000007A0851430A; GUID=0256304512-0000065536-
0000000122-0139543306; CallId=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11;
URI=sip:88881111112@192.0.2.12;transport=tcp
```

```
### CALL_NEW () from VVB to VXML server
```

```
189323: May 02 16:10:49.778 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-
149370661959432] Browser.makeRequest(): got encoded
uri=http://192.0.2.11:7000/CVP/Server?MSG_TYPE=CALL_NEW&CALL_DNIS=8888111111&CALL_ANI=sip%3A6000
6099%40..
```

Uitnodiging ingewilligd-VRU-been

```
1951: 192.0.2.11: May 10 2017 11:39:38.067 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=DIALOG_CALLBACK.5}
CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-
149438037789633 - [OUTBOUND]: Invitation accepted - ack'ing
```

Antwoord

```
1958: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-121-
SIP-19462} Sending BUS MSG for Event Reportnew CSS:[EVENT_REPORT] DialogID=0 SendSeqNo=0
EventID=ANSWER CauseCode=CAUSE_NONE
```

Bewerking van antwoorden vanaf SIP SS

4285: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from SIP_SS - [EVENT_REPORT] DialogID=0 SendSeqNo=0 EventID=ANSWER CauseCode=CAUSE_NONE

Publicatie van antwoorden aan UCCE

4286: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Publishing to UCCE - [EVENT_REPORT] DialogID=46 SendSeqNo=2 EventID=ANSWER CauseCode=NONE

Nieuwe oproep [IVR] - verwerking van VXServer - Nieuw gesprek met VRU + Correlatie-id

44242: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A [IVR] - processing from VXMLServer - [NEW_CALL]
ClientNewCallEvent,sessionId=0F46E580000100000000007A0851430A ani=sip:12345@192.0.2.11:5060 dnis=88881111112 uui= callId=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 seqNo=1 invokationId=0 message=null ccbServletUrl= ccbServletReqTimeout=0

Nieuwe Call-Publicatie naar ICM_SS

44243: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] [Publishing to ICM_SS] [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=88881111112 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0 serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables= ECC arrays= Peripheral Variables=

Nummerherkenning als correlatie

4287: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID = 0F46E580000100000000007A0851430A - Correlation ID routed call

[IVR-VRU_LEG_DIALOG]-verwerking van IVR_SS-[NEW_call]-VRU ID-been

4288: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from IVR_SS - [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=88881111112 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0 serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables= ECC arrays= Peripheral Variables=

[request_Instruction] publiceren naar UCCE

4289: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to UCCE - [REQUEST_INSTRUCTION] DialogID=47 SendSeqNo=1 ANI=12345 DNIS=88881111112

correlationId=12 trunkGroupId=200 trunkNumber=0 serviceId=2 uui= calledNumber= location=
locationpkid= pstntrunkgroupid= pstntrunkgroupchannelnum=0 sipheader=

[RUN_SCRIPT_REQ]-[IVR_VRU_LEG_DIALOG]-verwerking van UCCE

4294: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Processing from UCCE - [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V
scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201
rcday=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC
variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code:
0,user.microapp.app_media_lib: ..,user.microapp.media_server:
http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N,
ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=

[RUN_SCRIPT_REQ]-[IVR_VRU_LEG_DIALOG] - Uitgeven aan IVR_SS

4295: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Publishing to IVR_SS - [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V
scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201
rcday=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC
variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code:
0,user.microapp.app_media_lib: ..,user.microapp.media_server:
http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N,
ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=

[RUN_SCRIPT_REQ]-[IVR] verwerking van ICM_SS

44250: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-
149438037789633@192.0.2.11 [IVR] [processing from ICM_SS] [RUN_SCRIPT_REQ] DialogID=47
SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete
callguid=0F46E580000100000000007A0851430A rckey=201 rcday=152070 rcseq=1 uui= featureType=0
featureParam1= _featureParam2= ECC variables=user.media.id:
0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib:
..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input:
complete,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=

[RUN_SCRIPT_REQ]-[IVR]- Publicatie naar VXML-server

44251: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-
149438037789633@192.0.2.11 [IVR] - Publishing to VXMLServer - [RUN_SCRIPT_REQ] DialogID=47
SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete
callguid=0F46E580000100000000007A0851430A rckey=201 rcday=152070 rcseq=1 uui= featureType=0
featureParam1= _featureParam2= ECC variables=user.media.id:
0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib:
..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input:
complete,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,

Peripheral Variables=

VVB AUDIUM_Root(AUDIUM_VXML)

```
178107: May 02 16:07:47.410 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] application (Root document):  
/CVP/Server?audium_root=true&calling_into=HelloWorld
```

VVB ROOT-document

```
178424: May 02 16:07:56.480 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] VoiceBrowser.invokeRootDocument:  
[URI=http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld fragment=null]
```

VVB-lading en parsen

```
178430: May 02 16:07:56.481 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] VXMLDocumnet.loadbAndParse(): fetching  
(http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld) timeout attribute=0
```

VVB-browser dient een aanvraag in

```
178435: May 02 16:07:56.481 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.makeRequest(): got encoded  
uri=http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld
```

VVB Fetch VXML doc

```
178444: May 02 16:07:56.489 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.fetchVxml(): got doc from new VxmlDocStream(type: 1, cnt:  
com.cisco.wf.cache.http.CachedURLConnection:http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld, cachable: true, isFromCache: false, lastModified: 0)
```

###VVB successfully fetched

```
178445: May 02 16:07:56.489 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Successfully fetched bytes: 0, duration(s): 0.008, URI:  
http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld
```

VXML Content

Content of VXML Document

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<vxml version="2.0">
```

.....

VVB SUBMIT POST ()

```
178480: May 02 16:07:56.494 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): goto req=http://192.0.2.11:7000/CVP/Server
```

```
178481: May 02 16:07:56.494 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): req's method=post
```

Resultaat van de SUBMIT-post

178506: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Fetch: HTTP 200 OK
178507: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.fetchVxml(): got doc from new VxmlDocStream(type: 1, cnt: com.cisco.net.www.protocol.http.HttpURLConnection:http://192.0.2.11:7000/CVP/Server, cachable: false, isFromCache: false, lastModified: 0)
178508: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Successfully fetched bytes: 0, duration(s): 0.004, URI: http://192.0.2.11:7000/CVP/Server

Elementen handvatten

178603: May 02 16:07:56.509 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): goto req=http://192.0.2.11:7000/CVP/Server
178604: May 02 16:07:56.509 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): req's method=post

Maakt nieuwe Query

178510: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Content of POST query:
audium_vxmlLog=
178511: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:Content of VXML Document:
<?xml version="1.0" encoding="UTF-8"?>
<vxml version="2.0" application="/CVP/Server?audium_root=true&calling_into=HelloWorld">
<form id="audium_start_form">
<block>

Resultaat van post (audiolading)

178579: May 02 16:07:56.503 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] <audio> src:/CVP/audio/helloworld_audio.wav expr:
178580: May 02 16:07:56.503 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] checkWriteOnDiskForVVB: Setting Disk write to true for VVB

[RUN_SCRIPT_RESULT][IVR] - verwerking van VXMLerver

44257: 192.0.2.11: May 10 2017 11:39:50.927 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] - processing from VXMLServer - [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=0 Result=1 CED= newTransaction=0 ECC variables= ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR]-publicatie naar ICM_SS

44248: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] [Publishing to ICM_SS] [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR_VRU_LEG_DIALOG]-Verwerking van IVR_SS-Resultaat=1

4292: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from IVR_SS - [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR_VRU_LEG_DIALOG]-Publicatie naar UCCE

4293: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to UCCE - [RUN_SCRIPT_RESULT] DialogID=47 SendSeqNo=2 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

Agent wordt beschikbaar en ICM annuleert de VXML operatie

4296: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} 47CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE]sending ICMEvent, sessionId=0F46E580000100000000007A0851430A callId=null dialogId=47 sourceId=null systemType=ICM mediatype= dnis= ani= srcAddress= locationsiteid=sessionId=0F46E580000100000000007A0851430A callType=0 cacheCallContext=false postcallsurveycall=false icmMessage=DIALOGUE_FAILURE_CONF

[Dialog_error_conf]-[IVR_VRU_LEG_DIALOG publicatie naar UCCE]

4297: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to UCCE - [DIALOGUE_FAILURE_CONF] DialogID=47 SendSeqNo=3 InvokeId=2 ErrorCode=E_OPERATION_CANCELLED

[CANCEL]-verwerking van UCCE

4298: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from UCCE - [CANCEL] DialogID=47 SendSeqNo=3 InvokeID=3 ReqID=2

[Connect] verwerking van UCCE

4300: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from UCCE - [CONNECT] DialogID=46 SendSeqNo=2 Label=4001 TxrHint=false rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce= callguid=0F46E580000100000000007A0851430A ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143, Peripheral Variables=

[Connect] publicatie naar SIP_SS-label 4001

4301: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Publishing to SIP_SS - [CONNECT] DialogID=46 SendSeqNo=2 Label=4001 TxrHint=false rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce= callguid=0F46E580000100000000007A0851430A ECC variables=user.media.id:

0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib:
..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input:
complete,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=

Overeenkomende routeswitchgesteente

1968: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Static route matched 4001 to StaticRoute: patterns like 400> will route to
10.66.75.51
1969: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Using Local Static Route for sip:4001@10.66.75.51

VRU LEG-interconnects

4302: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Processing from UCCE - [RELEASE] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR

[Afsluiten] publiceren [losmaken]

4303: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID = 0F46E580000100000000007A0851430A, DLGID = 47 [IVR_VRU_LEG_DIALOGUE] -
Publishing [DISCONNECT] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR, LEGID =
0F46E580000100000000007A0851430A-149438037789633@192.0.2.11, DNIS = 888811111112, ANI = 12345

[Afsluiten] publicatie naar IVR_SS

4304: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Publishing to IVR_SS - [DISCONNECT] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR

VVB-ontbinding

178207: May 02 16:07:56.190 AEST %MIVR-SS_VB-7-UNK: [CALLID=43A31C0000010000000000790851430A-149370359030630] Content of POST query:

audium_vxmlLog=

178208: May 02 16:07:56.191 AEST %MIVR-SS_VB-7-UNK:Content of VXML Document:

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<vxml version="2.0">
```

```
<catch event="vxml.session.error">
```

```
<return event="vxml.session.error" />
```

```
</catch>
```

```
<catch event="telephone.disconnect.hangup">
```

188680: May 02 16:10:49.431 AEST %MIVR-SS_VB-7-UNK: [CALLID=43A31C0000010000000000790851430A-149370359030630] traverseDialog: id=Disconnect

196326: May 10 11:21:40.066 AEST %MIVR-JASMIN-7-UNK: [CALLID=0F46E580000100000000007A0851430A-149438037789633] SIP-ltp6-88881111*, State=CONNECTED: setDisconnected processTerminated, cause=NORMAL

Ring rugbeen

1972: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Static route matched 91919191 to StaticRoute: patterns like 91919191> will route to 192.0.2.12

1973: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Using Local Static Route for sip:91919191@192.0.2.12

Uitnodigen tot VXML GW

1978: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039066134 - [OUTBOUND]: INVITE TO <sip:91919191@192.0.2.12;transport=tcp> FROM "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[10] 100REL[Unsupported]

Sending Message (NB): INVITE sip:91919191@192.0.2.12;transport=tcp SIP/2.0

Via: SIP/2.0/TCP 192.0.2.11:5060;branch=z9hG4bKkIR8MEBv53bzAj6MuGd1vw~~132

Max-Forwards: 67

To: <sip:91919191@192.0.2.12;transport=tcp>

From: "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060>;tag=ds789c1a64

Call-ID: 0F46E580000100000000007A0851430A-149438039066134@192.0.2.11

CSeq: 1 INVITE

Content-Length: 0

Contact: <sip:12345@192.0.2.11:5060;transport=tcp>

Expires: 10

User-Agent: CVP 11.5 (1) ES-1 Build-344

Call-Info: <sip:10.66.74.114:5060>;purpose=x-cisco-origIP

Remote-Party-ID: "PSTN PHONE--CVP_11_5_1_0_1_0_344"

<sip:12345@192.0.2.11>;party=calling;screen=yes;privacy=off

Date: Wed, 10 May 2017 01:17:58 GMT

Min-SE: 1800

Allow: INVITE, OPTIONS, BYE, CANCEL, ACK, PRACK, UPDATE, REFER, SUBSCRIBE, NOTIFY, INFO, REGISTER

Allow-Events: telephone-event

X-Cisco-CCBProbe: id:192.0.2.14;loc:donnielab;trunks:10

Session-Expires: 1800

Cisco-Gucid: 0F46E580000100000000007A0851430A

Supported: timer

Supported: resource-priority

Supported: replaces

Supported: sdp-anat

App-Info: <192.0.2.11:7000:7443>;ringtone=ringback.wav

Ringback tone met de beller wordt gemaakt

2007: 192.0.2.11: May 10 2017 11:39:50.771 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-128-SIP-19468} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039066134 - [RING-OUT]: Notifying that ringtone is established 200 OK with caller.

Agent Bene uitgenodigd op CUCM

2013: 192.0.2.11: May 10 2017 11:39:50.771 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039077135 - [OUTBOUND]: INVITE TO <sip:4001@10.66.75.51;transport=tcp> FROM "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[60] 100REL[Unsupported]

Aangesloten oproepen

2049: 192.0.2.11: May 10 2017 11:39:58.817 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-130-

SIP-19471} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039077135 - [OUTBOUND]: Acked the invite.

Gerelateerde informatie

- [Technische ondersteuning en documentatie – Cisco Systems](#)