

يئاقتنال تاملكملا هيچوت ةداعا نيوكت Webex ربع لاصتال

تايوتحمل

[ةمدقملا](#)

[ةيساسال تابلطتملا](#)

[تابلطتملا](#)

[ةمدختسملا تانوكملا](#)

[ةيساسا تامولعم](#)

[تاملكملا راطتنا ةمئاق](#)

[قلودج](#)

[يئاقتنال تاملكملا هيچوت](#)

[يئاقلتال درلا](#)

[قلودج](#)

[يئاقتنال تاملكملا هيچوت](#)

[قلطع](#)

[قلودج](#)

[يئاقتنال تاملكملا هيچوت](#)

[قلص تاذا تامولعم](#)

ةمدقملا

يئاقلتال درلل يئاقتنا تاملكملا هيچوت ةداعال ةيساسال ةفيظولا دنتسملا اذه فصبي
ةلثمال ضعب مدقويو تاملكملا راطتنا ةمئاقو.

ةيساسال تابلطتملا

تابلطتملا

ةيلاتال عيضاوملاب ةفرعم كيديل نوكت ناب Cisco ي صوت:

- ةلودجلاو تاملكملا راطتنا ةمئاقو يئاقلتال درلا لثم تازيمل يساسال مهفال
- ةسسؤملا ي لوؤسملا راودا بعل
- هنيوكت بجي امل حضاو مهفب عتمتت نا
- ةبولطملا تازيملل نيعملا طشنال فاتاهل مقرر

ةمدختسملا تانوكملا

Control Hub لى دنتسملا اذه في ةدراوال تامولعملا دنتست

ةصاخ ةيلمعم ةئيب في ةدوجوملا ةزهجال نم دنتسملا اذه في ةدراوال تامولعملا عاشن م

تنالك اذا (يضا رتفا) حوسمم نيوكتب دنتسمل اذه يف ةمدختسُمل ازهجال ايمج تادب رما يال لمحتمل ريثاتلل كمهف نم دكاتف، ليغشتل دي قكتكبش

ةيساسا تامولعم

يئاقللتل درلل يئاقنتا تاملكمل هيحوت ةداعل ةيساسالا ةفيظولا دنتسمل اذه فص ي تسيل ةلثمألل ةمدقملا لولحل نا ظحال. ةلثمألا ضعب مدقويو تاملكملا راطنتا ةمئاقو يلمعل امدختسا واهتطاسب يه ةلثمألا هذه ةمقي. فدهل قيقحتل ةديحولل ققيرطلا

حيحت. تاملكملا راطنتا ةمئاقو يئاقللتل درلا عاشن راخي لىل Webex ربع لاصتالا يوتحي لىل ادانتسا تاملكملا نوقلتل نيذل ءالكول نم تاعومجم ميظنت تازيملا هذه كل نيوكتل.

نم ديدعل كانه، تاملكملا هيحوت ةداعل يئاقنتالا نيوكتل نم ققحتل دعب: ةظحال م تي. يئاقللتل درلل تاملكملا هيحوت ةداعل ديدحت يف اهن ييغت مت يتل ريياعملا تاعاس يتات، ةلاحلا هذه يف. هب اهدرس مت يذل رمال لىل ادانتسا ريياعملا نم ققحتل اذو، الو لمعل تاعاس نم ماظنل ققحتي امدنع، يلاتلابو. ةلطلعل لبق لمعل مسا ثيدحت حرتقملا نم. ةيلاتل ريياعملا نم ققحتي دوعي ال هناف، طرشلل يفوتسا، لاثملا لىبس لىل. الو ةلطلعل ريياعم نم ققحتل متي ثيحب ماقرالاب ريياعملا، كلذ لىل امو 02_Business و 01_Holiday.

تاملكملا راطنتا ةمئاق

ي: امك لمعت ةدراطم ةعومجم كي دل نوكي نا بح ي، ةلثمألا هذه:

- تاملكملا راطنتا مئاقو ءالكو لىل ةدراول تاملكملا هيحوت متي: لمعل تاعاس اناثأ
- (يلا مويلا نم احابص 09:00 ةعاسلا لىل ءاسم 5:00 ةعاسلا نم) لمعل تاعاس دعب: نيم مدختسمل يتوصلل ديربل لىل ةدراول تاملكملا هيحوت متي.

ةعاسلا نم) PM لودجل ةيئاقنتا هيحوت ةداعل ةدعاق عاشن يه كلذ قيقحتل ققيرط لصف أو هيحوت ةداعل ةدعاقو، مويلا كلذ دعب لمعل تاعاس ةيطغت لجا نم (م 11:59 ةعاسلا لىل 5:30 امه يلك لىل بح ي). (ص 8:59 لىل ص 12:00 نم) يلاتل مويلا يف لمعل مدع تاعاسل ةيئاقنتا يتوصلل ديربل لىل تاملكملا هيحوت ةداعل.

ةلودج

لاثملا اذهل ني لودج عاشن بح ي:

- 11:59 لىل 5:30 نم: لمعل تاعاس دعب مويلا ةيقب ي طغت يتل ةعاسلا دعب ام تاعاس "PM هيحوت ةداعل" يه هذه. ءاسم.
- ةعاسلا لىل احابص 12:00 ةعاسلا نم: لمعل تاعاس لبق تقول ي طغت يتل تاعاسلا. 'هيحوتل ةداعل' يه هذه. احابص 8:59.

ةلودج او ديصلا ةعومجم عقوم لىل لاقنتالا بح ي، ني لودجلا ني لودجلا عاشن ل. 1. ةوطخل

MXC Test
United States
Location ID: e2d8e222-0d57-4ee4-8988-1b3a643d8468

Overview

Main Number +12025550138 >

PSTN Connection Cloud Connected PSTN - Intelpeer (US non-integrated): [Manage](#)

Emergency Calling

Emergency Callback Number ⚠ Location main number >

Emergency Location Identifier eli >

Emergency Call Notification Off >

Enhanced Emergency Calling ⚠ Off >

Call Settings

Scheduling >

Voicemail >

Voice Portal >

لوجد ة فاضا رتخأ 2. ةوطخل.

MXC Test Business Hours
United States
Location ID: e2d8e222-0d57-4ee4-8988-1b3a643d8468

[Overview](#) > [Scheduling](#)

Scheduling

Scheduling is used to support other calling features, such as auto attendants. A time schedule establishes slots of time, during which a feature can execute specific behavior.

[Add Schedule](#)

[Export](#)

ةروصلا هذه يف حضوم وه امك PM هيجوت ةداعا لوجد عاشناب مق 3. ةوطخل.

Schedule Name

Enter a name to identify the schedule.

PM forwarding X

Schedule Type

Select the type of schedule that you want to add.

Business Hours Holiday

Schedule

The new schedule shows a default entry. You can modify the schedule to fit your organization's needs.

Sunday

Monday 5:30 PM to 11:59 PM

Tuesday 5:30 PM to 11:59 PM

Wednesday 5:30 PM to 11:59 PM

Thursday 5:30 PM to 11:59 PM

Friday 5:30 PM to 11:59 PM

Saturday

ظفحرقنا 4. ةوطخال

ةروصللا هذه يف حضوم وه امك AM هيچوت ةداعإ لودج عاشنإب مق 5. ةوطخال

Schedule Name

Enter a name to identify the schedule.

AM Forwarding



Schedule Type

Select the type of schedule that you want to add.

Business Hours Holiday

Schedule

The new schedule shows a default entry. You can modify the schedule to fit your organization's needs.

Sunday

Monday to

Tuesday to

Wednesday to

Thursday to

Friday to

Saturday

12:00 ةعاسلا نم ةدعاقلا قيبتت كي لع ب جي ، دحل او تبسلا يموي لمعت مل اذا 6 ةوطخلا هلمك أب موي لل هي جوتلا ةداع اذه قبطي . ءاسم 11:59 ةعاسلا ىلا احابص

Enter a name to identify the schedule.

AM Forwarding



Schedule Type

Select the type of schedule that you want to add.

Business Hours

Holiday

Schedule

The new schedule shows a default entry. You can modify the schedule to fit your organization's needs.

<input checked="" type="checkbox"/>	Sunday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="11:59 PM"/>
<input checked="" type="checkbox"/>	Monday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="8:59 AM"/>
<input checked="" type="checkbox"/>	Tuesday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="8:59 AM"/>
<input checked="" type="checkbox"/>	Wednesday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="8:59 AM"/>
<input checked="" type="checkbox"/>	Thursday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="8:59 AM"/>
<input checked="" type="checkbox"/>	Friday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="8:59 AM"/>
<input checked="" type="checkbox"/>	Saturday	<input type="text" value="12:00 AM"/>	to	<input type="text" value="11:59 PM"/>

Lunch Break

ظفحرقنا 7. ةوطخل

يهتني، (ةعاسلا دعب ام تاعاسل) يئاقتنا تاملكملا هي جوت ةداعا لودج ناك اذا: ةظحالم احابص 08:59:59 ةعاسلا دعب اهؤارج متي يتلا تاملكملا نإف، احابص 8:59 ةعاسلا يف هي جوت ةداعا ليغشتب موقت ال، احابص 08:59:01 ةعاسلا يف، لاثملا لابس يلع لمعل تاعاس يلى تاملكملا هي جوت متي كلذ نم الدبوتاملكملا

يئاقتنا تاملكملا هي جوت

يئاقتنا "تاملكملا هي جوت ةداعا" عطقملا يف تاملكملا راطتنا ةمئاق يلى لودجال نييغت تاملكملا هي جوت ةداعاو تاملكملا راطتنا ةمئاق يلى لقتنا 1. ةوطخل

Call queue



Overview

Enable Call Queue



Settings

Manage >

Phone Number

1150 or +12025550149 >

Call Forwarding

Disabled >

Agents

Manage >

Call Routing Pattern

Top Down >

Overflow Settings

Manage >

Bounced Calls

Manage >

Announcements

Manage >

Announcement Files

Manage >

ةداعإ متي يذلا فتاهل مقرر رايتخإ بجي .ايئاقنتنا تاملكملا هي جوت ةداعإ رتخأ 2. ةوطخل لاسررا يف بغيرت تنك اذإ يتوصلال ديربل رايتخ نم ققحتل بجي .هيل تاملكملا هي جوت يتوصلال ديربل إلى تاملكملا .



Call queue

Cancel

Save

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.



Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.



Send to voicemail



لوال لودجلل ريرحت رتخأ 3. ةوطخل

هي جوتل ةداعإ متي ،ةلاحل هذه يف .ةدعاقلل هئاشناب تمق يذلا لودجل رتخأ 4. ةوطخل

Edit When to Forward

×

Call Forwarding Selective Details

Rule Name

AM forwarding

×

When To Forward

Calls will be forwarded according to the schedule set here.

Business Hours Schedule

AM Forwarding

∨

Holiday Schedule

None

∨

Schedule

Friday:	Weekly	Friday, 12:00 AM to 8:59 AM
Monday:	Weekly	Monday, 12:00 AM to 8:59 AM
Saturday:	Weekly	Saturday, 12:00 AM to 11:59 PM
Sunday:	Weekly	Sunday, 12:00 AM to 11:59 PM

[Show More](#)

Forward To

Enter the number that your calls will be forwarded to.

Default Phone Number

+12025550139

Different Phone Number

Calls From

Calls from the number(s) defined here will be forwarded.

Any Number

Cancel

Save

5. (لقطع اب ةصاخ، ةديج ةدعاق عاشنإ يمازلإل نم ف، ال او) راتخم ةلطف لودج دجوي ال 5 ةوطخل

ةداعإ يف هرايتخإ مت يذلا يضارتف ال مقرلا لىل هيجوتل ةداعإ نييعت مت 6 ةوطخل لاصتال هيجوت

ةدعاق لل مقر ي نم تاملكملا قيبطت متي 7 ةوطخل

ظفح قوف رقنا 8 ةوطخل

ءارزولا سيئر جم انرب يف هسفن رمال او زجت نا بجيو 9 ةوطخل

Add When to Forward

Call Forwarding Selective Details

Rule Name

PM Forwarding



When To Forward

Calls will be forwarded according to the schedule set here.

Business Hours Schedule

PM forwarding



Holiday Schedule

None



Schedule

Friday:	Weekly	Friday, 5:30 PM to 11:59 PM
Monday:	Weekly	Monday, 5:30 PM to 11:59 PM
Thursday:	Weekly	Thursday, 5:30 PM to 11:59 PM
Tuesday:	Weekly	Tuesday, 5:30 PM to 11:59 PM

[Show More](#)

Forward To

Enter the number that your calls will be forwarded to.

Default Phone Number

+12025550139

Different Phone Number

Calls From

Calls from the number(s) defined here will be forwarded.

Any Number

Cancel

Save

ظفح رتخأ 10. ةوطخل

ةروصل هذه يف تاملكملا هيجوت ةداعإ ضرع متي

Call queue



Cancel

Save

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.



Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.

Q +12025550139 X

Send to voicemail

Enable Rule	Rule Name	Rule Type	Incoming Calls From	Incoming Calls To	Actions
<input checked="" type="checkbox"/>	AM forwarding	Forward	All calls	Primary	Edit
<input checked="" type="checkbox"/>	PM Forwarding	Forward	All calls	Any Number	Edit

[+ Add When to Forward](#)

[+ Add When Not to Forward](#)

ظفح رتخأ. 11 ةوطخل

يئاقلتل درلا

يئاقلتل درلا لمدعي يئاقلتل درلا نوكل نأ بچي:

- يئاقلتل درلا ةمئاق ليغشت متي: لمعل تااعاس ةانثأ
- (يئاقلتل مويل نم احابص 09:00 ةاعاسلا إلى ةاعاسلا نم) لمعل تااعاس دعب
نعم مدختسمل يتوصلل ديربل إلى ةراول تاملكملا هيحوت متي

قباسلا لاثملا ةلثامم، ةيئاقلتل نا هيحوت ةداعإ ةاشنإ يه كلذ قيقحتل ةقيرط لصفأو
تاملكملا راطتلا ةمئاقلتل

لودج لخادت مدع نم دكأتلا بچي. لعفلاب هنيوكت مت لودج يئاقلتل درلا ىدل: ةظحالم
يئاقلتل لاصتالا هيحوت ةداعإ

لودج رتخأ، يئاقلتل درلا ي ف. 1 ةوطخل

AA Cisco PSTN test



Overview

Enable Auto Attendant 

General Settings

Manage >

Phone Numbers

1713 or +12093081713 >

Call Forwarding

Disabled >

Dialing Options

Organization >

Business Hours Auto Attendant

Schedule

New schedule >

Menu

Manage >

Greeting

Default Greeting >

After Hours Auto Attendant

Menu

Manage >

Greeting

1661978417587.wav >

احابص 9:00 ةاسلا نم ةمچلا إلى نينثالا نم ينمزلال لودجال نيي عت متي، لاثملا اذ في
ءاسم 5:00 ةاسلا إلى

AA Cisco PSTN test

[Overview](#) > Business Hours Schedule

Business Hours Schedule

Set the hours during which your Business Hours Auto Attendant operates. Your After Hours Auto Attendant operates during all the remaining non-business hours.

Assign an existing schedule

BH schedule 

Schedule

Friday:	Weekly	Friday, 9:00 AM to 5:00 PM
Monday:	Weekly	Monday, 9:00 AM to 5:00 PM
Thursday:	Weekly	Thursday, 9:00 AM to 5:00 PM
Tuesday:	Weekly	Tuesday, 9:00 AM to 5:00 PM
Wednesday:	Weekly	Wednesday, 9:00 AM to 5:00 PM


Create a new schedule

ۆلۆدج

للااملا اذهل نيلولولاج عاشنل ابحي

- للىءاسم 5:01 نملعلالاعاس دعب مويللا ةيقب يطلع الالاعاس الال دعب امالاعاس للىءاسم 11:59 "PM ةجول ةءاع" لىه هءه .
- ةالال للىءاسم 12:00 ةالال نملعلالاعاس لبق القولال يطلع الالاعاس الال . احابص 8:59 'ةجول ةءاع' لىه هءه . احابص

ۆلۆدجلا رايلءا ةئالقلا للال لال ةقوم لىل للاقلا لال ابحي . 1 ةولءالا





Cisco PSTN test
United States
Location ID: 380ee403-ec07-4da0-b233-bfd602ee2db7

Overview

Main Number	+12093081713	>
PSTN Connection	Cisco PSTN - Cisco Calling Plans (US): Manage	

Emergency Calling

Emergency Callback Number	 Location main number	>
Emergency Location Identifier	eli	>
Emergency Call Notification	Off	>
Enhanced Emergency Calling	 Off	>

Call Settings

Scheduling	>
Voicemail	>

PM ةجول ةءاع لولء عاشنل اولولء ةفابصا رلءا . 2 ةولءالا

Cancel

Save

Schedule Name

Enter a name to identify the schedule.

PM forwarding



Schedule Type

Select the type of schedule that you want to add.

Business Hours

Holiday

Schedule

The new schedule shows a default entry. You can modify the schedule to fit your organization's needs.

Sunday

Monday

⌚ 5:01 PM



to

⌚ 11:59 PM



Tuesday

⌚ 5:01 PM



to

⌚ 11:59 PM



Wednesday

⌚ 5:01 PM



to

⌚ 11:59 PM



Thursday

⌚ 5:01 PM



to

⌚ 11:59 PM



Friday

⌚ 5:01 PM




to

⌚ 11:59 PM



Saturday

 AA لودج يهتني شيح ءاسم 05:01 ءاسم لادب نأ بجي .لخادتل مدع مهم لآ نم :ءظحالآ ءاسم 5:00 ءاسم لآ ف

طفا رتخأ 3. ءوطخال

ص 8:59 لآ ص 12:00 نم ءرتفلل ،AM لودج ءاشنإ 4. ءوطخال

Cancel

Save

Schedule Name

Enter a name to identify the schedule.

AM Forwarding



Schedule Type

Select the type of schedule that you want to add.

Business Hours

Holiday

Schedule

The new schedule shows a default entry. You can modify the schedule to fit your organization's needs.

Sunday

Monday

🕒 12:00 AM



to

🕒 8:59 AM



Tuesday

🕒 12:00 AM



to

🕒 8:59 AM



Wednesday

🕒 12:00 AM



to

🕒 8:59 AM



Thursday

🕒 12:00 AM



to

🕒 8:59 AM



Friday

🕒 12:00 AM




to

🕒 8:59 AM



Save. راتخن 5. ةوطخلال

 يهتني، (ةعاسلا دعب ام تااعاسل) يئاقتنا تاملكملا هيحوت ةداعإ لودج ناك اذا: ةظحالم موقت ال، احابص 08:59:01 ةعاسلا يف، لاثملا ليبس يلع، احابص 8:59 ةعاسلا يف ال تاملكملا هيحوت متي كلذ نم ال دبو تاملكملا هيحوت ةداعإ ليغشتب تاملكملا لمعلا تااعاس.

يئاقنتال تاملكملا هيحوت

يئاقنتال لكش ب يئاقنتال درلا اعادتسإ هيحوت ةداعإ ةي نمزلال لودجال ني عتت مق


تاملكملا هيحوت ةداعإ رتخاو يئاقنتال درلا ال لقتنا 1. ةوطخلال

AA Cisco PSTN test



Overview

Enable Auto Attendant 

General Settings 

Manage >

Phone Numbers

1713 or +12093081713 >

Call Forwarding

Disabled >

Dialing Options

Organization >

Business Hours Auto Attendant

ةيئاقتنالال هيجوتال ةداعإ تاملكم رتخاواهنينكمتب مق 2. ةوطخال

AA Cisco PSTN test



Cancel

Save

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.



Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.

Send to voicemail

إلى لاسررا راخ ددحو هيلإ تاملكم ال هيجوت ةداعإ إلى جاتحت يذل مدختسم ال رتخأ 3. ةوطخال
يتوصل ال ديرب ال إلى ةرشابم تاملكم ال لقتنت كذل، يتوصل ال ديرب ال

اقبسم هئاشناب تمق يذل لودج ال رتخاوا AM هيجوت ةداعإ لودج فضا 4. ةوطخال

(دايالاب ةصاخ ةديج ةدعاق ءاشنإ يمازلإ نم ف، الإ) راتخم ةلطمع لودج دجوي ال 5. ةوطخال

Edit When to Forward

×

Call Forwarding Selective Details

Rule Name

AM Forwarding

×

When To Forward

Calls will be forwarded according to the schedule set here.

Business Hours Schedule

AM Forwarding

∨

Holiday Schedule

None

∨

Schedule

Friday:	Weekly	Friday, 12:00 AM to 8:59 AM
Monday:	Weekly	Monday, 12:00 AM to 8:59 AM
Thursday:	Weekly	Thursday, 12:00 AM to 8:59 AM
Tuesday:	Weekly	Tuesday, 12:00 AM to 8:59 AM

[Show More](#)

Forward To

Enter the number that your calls will be forwarded to.

Default Phone Number

Different Phone Number

5849

×

Calls From

Calls from the number(s) defined here will be forwarded.

Any Number

Cancel

Save

PM. لودج ة فاضا. 6 ة وطلخا

(داي ة ألاب ة صاخ ة دي دج ة د عاق ة اش نإ يمازل إال نم ف ، إا و) راتخم ة ل طع لودج دجوي ال . 7 ة وطلخا

Add When to Forward

×

Call Forwarding Selective Details

Rule Name

PM Forwarding

×

When To Forward

Calls will be forwarded according to the schedule set here.

Business Hours Schedule

PM forwarding

∨

Holiday Schedule

None

∨

Schedule

Friday:	Weekly	Friday, 5:01 PM to 11:59 PM
Monday:	Weekly	Monday, 5:01 PM to 11:59 PM
Thursday:	Weekly	Thursday, 5:01 PM to 11:59 PM
Tuesday:	Weekly	Tuesday, 5:01 PM to 11:59 PM

[Show More](#)

Forward To

Enter the number that your calls will be forwarded to.

Default Phone Number

+12096995310

Different Phone Number

Calls From

Calls from the number(s) defined here will be forwarded.

Any Number

Selected Phone Numbers

Cancel

Save

ةروسلا هذه فةلودجملا فئاقلا لدرلا تادادع رهظت 8 ةوطخلا

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.



Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.

Q +12096995310 X

Send to voicemail

Enable Rule	Rule Name	Rule Type	Incoming Calls From	Incoming Calls To	Actions
<input checked="" type="checkbox"/>	AM Forwarding	Forward	All calls	Primary	Edit
<input checked="" type="checkbox"/>	PM Forwarding	Forward	All calls	Any Number	Edit

[+ Add When to Forward](#)

[+ Add When Not to Forward](#)

ةل طع

ةلصفنم ةدعاق عاشنإ به ةددم تالطعل ةاقتنم هيجوتل ةداعل لعجل ةقيرط لصفأ

يئاقلتل درلل مدختسمل لاثمل ل سفن لي اميف

عم تالطعل اناثأ رخآ مقرىل ا هيجوت ةداعل تمت يئاقلتل درل تاءاعدتسإ ديرت تنأ لودجل اذ:

- داليمال ديع ةلئل لال خ
- ربمفون نم نيضامال ني عوبسأل لال خ

ةل طع لودج عم ةيئاقتنم هيجوت ةداعل عاشنإ به كذ ققيرط لصفأ

ةل و دج

ةل و دج لال رتخأ. ةل طعل ل لودج عاشنإ ب مقو يئاقلتل درل ع قوم لىل لقتنا 1. ةوطخل

MXC Test
United States
Location ID: e2d8e222-0d57-4ee4-8988-1b3a643d8468

Overview

Main Number +12025550138 >

PSTN Connection Cloud Connected PSTN - Intelepeer (US non-integrated): [Manage](#)

Emergency Calling

Emergency Callback Number ⚠ Location main number >

Emergency Location Identifier eli >

Emergency Call Notification Off >

Enhanced Emergency Calling ⚠ Off >

Call Settings

Scheduling >

Voicemail >

Voice Portal >

لودج ة فاضا قوف رقنا 2. ةوطخلا

ةل طعك عونلا رتخاو ةل طعل مايا لودج ةي مستب مق 3. ةوطخلا

Location ID: e2d8e222-0d57-4ee4-8988-1b3a643d8468

Cancel Save

Schedule Name
Enter a name to identify the schedule.
Holiday Schedule X

Schedule Type
Select the type of schedule that you want to add.
 Business Hours Holiday

Schedule

خيراتلا بسحو مويلا لاوط رتخاو داليملا ديعل ةل طع ءاشناب مق 4. ةوطخلا

Schedule

You can add multiple instance of events that define this schedule.

Export

Event Name ▲	Repeat	Start time	End time	Actions
				Edit

Holiday name

Christmas

Recurrence

Yearly

All Day

By

Date

On

25

of

December

Holiday Duration

ⓘ

Note: Event start date will always take the date specified above.

From

Dec 25, 2022

to

Dec 25, 2022

Cancel

Save

مذخست تنك اذ، كلذ عمو. يونسلا راركتلا رايتخاب موقت، لاثملا اذه يف: ةظحالم
ديج لكشب لمعت ةزيملنا ف، لقحلا اذه يف ءيش ال وأ راركتلا

ظفح قوف رقنا 5 ةوطخلا

لودجال سفن بجومب ربمفون نم نيريخال نيوعوبسألل ةلطلعلا ءاشنإ 6 ةوطخلا

Cisco PSTN test

United States

Location ID: 380ee403-ec07-4da0-b233-bfd602ee2db7

Overview > Scheduling > Edit Schedule

Schedule Name

Holiday

Schedule Type

Holiday

Schedule

You can add multiple instance of events that define this schedule.

Export

Event Name ▲	Repeat	Start time	End time	Actions
Christmas	Yearly	Dec 25, 2022	Dec 25, 2022	Edit

+ Add New Event

ربمفون 21 نم ةرتفللا يطغت، لاثملا اذه يف. اهمادختسا ديرت يتلا خيراوللا رتخأ 7 ةوطخلا

"رېم فون نم نېرې خأل نې عوبسأل" رېم فون 30 ىل

Schedule

You can add multiple instance of events that define this schedule.

Export

Event Name ▲	Repeat	Start time	End time	Actions
Christmas	Yearly	Dec 25, 2022	Dec 25, 2022	Edit

Holiday name

November holiday

Recurrence

None

All Day

Holiday Duration

ⓘ

From to

Cancel Save

11 : 59 PM

ظفح قوف رقنا 8. ةوطخل

ةجيتنل هذه ةروصل رهظت 9. ةوطخل



Cisco PSTN test

United States

Location ID: 380ee403-ec07-4da0-b233-bfd602ee2db7

×

Overview > Scheduling > Edit Schedule

Schedule Name

Holiday

Schedule Type

Holiday

Schedule

You can add multiple instance of events that define this schedule.

Export

Event Name ▲	Repeat	Start time	End time	Actions
Christmas	Yearly	Dec 25, 2022	Dec 25, 2022	Edit
November holiday	None	Nov 21, 2022	Nov 30, 2022	Edit

[\(+\)](#) Add New Event

يئاقتنال تاملكملا هيچوت

يئاقتنال لكش ب يئاقلنل دلل اعادتس! هيچوت ةداعل ةينمزل لوادجل نېي عت ب مق

تمام الكمال هي جوت دعاء رتخا و يئاق ل لتال درلا الى لقتنا 1. ةوطخل

AA Cisco PSTN test ✕

Overview

Enable Auto Attendant ✓

General Settings Manage >

Phone Numbers 1713 or +12093081713 >

Call Forwarding Enabled >

Dialing Options Organization >

Business Hours Auto Attendant

ةداعل تقو ةفاضل قوف رقنلا كنكمي، AM و PM ل دعاوقل عاشناب تمق نأ ذنم 2. ةوطخل
ةلطللل كب ةصاخلا ةديجلا ةدعاقلا عاشناب ل هي جوتال

AA Cisco PSTN test ✕

Overview > Call Forwarding

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.

✓

Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.

✕ Send to voicemail

Enable Rule	Rule Name	Rule Type	Incoming Calls From	Incoming Calls To	Actions
<input checked="" type="checkbox"/>	AM Forwarding	Forward	All calls	Primary	Edit ✕
<input checked="" type="checkbox"/>	PM Forwarding	Forward	All calls	Any Number	Edit ✕

Add When to Forward Add When Not to Forward

عقوملل هئاشناب تمق يذلا تالطلال لودج عم مويلا ل اوط موي لك رتخا 3. ةوطخل

Add When to Forward

×

Call Forwarding Selective Details

Rule Name

Holiday

×

When To Forward

Calls will be forwarded according to the schedule set here.

Business Hours Schedule

Every Day All Day

↓

Holiday Schedule

Holiday

↓

Schedule

Christmas:	Yearly	December 25, All Day
November holiday:	No Recurrence	November, 21, 12:00 AM to 11:59 PM

Forward To

Enter the number that your calls will be forwarded to.

Default Phone Number

+12096995310

Different Phone Number

Calls From

Calls from the number(s) defined here will be forwarded.

Any Number

Selected Phone Numbers

Calls To

Calls to the number(s) defined here will be forwarded.

Select a number

↓

Cancel

Save

تالطعلا لودج ةحص نم ققحتلا بجي. 4 ةوطخلا

Holiday Schedule

Holiday

↓

Schedule

Christmas:	Yearly	December 25, All Day
November holiday:	No Recurrence	November, 21, 12:00 AM to 11:59 PM

ظفح قوف رقنا. 5 ةوطخلا

ل ب ،ةعاسلا دع ب ام تاعاسل هيچوت ةداع| ديدحت ىلع يئاقولتلا درلا رود رصتقي ال ،نآلاو ةددحم تالطع اضيأ لمشي

AA Cisco PSTN test



Overview > Call Forwarding

Call Forwarding

Call Forwarding is a feature that allows the user to redirect the incoming call to another number based on schedules or preference.



Always Forward Calls

Selectively Forward Calls

An incoming call is forwarded or not forwarded to this number, based on the defined criteria.

Q +12096995310 X

Send to voicemail

Enable Rule	Rule Name	Rule Type	Incoming Calls From	Incoming Calls To	Actions
<input checked="" type="checkbox"/>	AM Forwarding	Forward	All calls	Primary	Edit
<input checked="" type="checkbox"/>	Holiday	Forward	All calls	Any Number	Edit
<input checked="" type="checkbox"/>	PM Forwarding	Forward	All calls	Any Number	Edit

ةلص تاذا تامولعم

- [مكحتلا ةحول ي ف يئاقولتلا روضحلا ةرادا](#)
- [Control Hub ي ف ديصلا تاعومجم ةرادا](#)
- [Cisco Webex Control Hub ي ف هنيوكتو لودج عاشنا](#)
- [Cisco نم تاليزنتلا او ي نقتلا معدلا](#)

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذه Cisco تچرت
ملاعلاء انءمچ يف نيمدختسمل معدى وتحم مي دقتل ةيرشبلاو
امك ةقيد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچرئ. ةصاغل مهتغب
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه
ىلإ أمئاد عوچرلاب يصوت وتامچرتل هذه ةقदन ةتيلوئسم Cisco
Systems (رفوتم طبارلا) يلصلأل يزلچنلإل دن تسمل